# **SIEMENS**

Data sheet 3RT2016-4AG62



CONTACTOR, AC-3, 4KW/400V, 1NC, AC 100V 50HZ, 100...110V 60HZ 3-POLE, SZ S00 RING CABLE LUG CONNECTION

	SIRIUS
	3RT2 contactor
V	690
	3
kV	6
	30 000 000

Degree of pollution		3
Surge voltage resistance Rated value	kV	6
Mechanical service life (switching cycles)		
<ul> <li>of the contactor typical</li> </ul>		30 000 000
<ul> <li>of the contactor with added electronics- compatible auxiliary switch block typical</li> </ul>		5 000 000
<ul> <li>of the contactor with added auxiliary switch block typical</li> </ul>		10 000 000
Thermal short-time current restricted to 10 s	Α	72
Protection class IP		
• on the front		IP20
• of the terminal		IP20
Equipment marking		
• acc. to DIN EN 61346-2		Q
• acc. to DIN EN 81346-2		Q

Main circuit:	
Number of poles for main current circuit	3
Number of NC contacts for main contacts	0
Number of NO contacts for main contacts	3
Operating voltage	

Operating ourrent         • at AC-1         — at 400 V at ambient temperature 40 °C         A         22           Rated value         — up to 690 V at ambient temperature 40 °C         A         22           Rated value         — up to 690 V at ambient temperature 60 °C         A         20           Rated value         — at 600 V Rated value         A         9           • at AC-2         — at 400 V Rated value         A         9           — at 400 V Rated value         A         7.7           — at 600 V Rated value         A         6.7           • at AC-4 at 400 V Rated value         A         8.5           Operating current with 1 current path         • at DC-1         — at 24 V Rated value         A         20           — at 110 V Rated value         A         2.1         — at 220 V Rated value         A         0.8           — at 220 V Rated value         A         0.6         — at 400 V Rated value         A         0.6           • at DC-3 at DC-5         — at 24 V Rated value         A         20         — at 24 V Rated value         A         20           • at DC-1         — at 220 V Rated value         A         1.6         — at 220 V Rated value         A         1.6           • at DC-3 at DC-5 — at 24 V Rated valu	<ul> <li>at AC-3 Rated value maximum</li> </ul>	V	690
— at 400 V at ambient temperature 40 °C Rated value  — up to 690 V at ambient temperature 40 °C Rated value  — up to 690 V at ambient temperature 60 °C Rated value  — up to 690 V at ambient temperature 60 °C Rated value  • at AC-2 at 400 V Rated value  • at AC-3  — at 400 V Rated value  — at 590 V Rated value  — at 590 V Rated value  — at 690 V Rated value  — at 690 V Rated value  — at 24 V Rated value  — at 110 V Rated value  — at 400 V Rated value  — at 400 V Rated value  — at 220 V Rated value  — at 220 V Rated value  — at 24 V Rated value  — at 440 V Rated value  — at 440 V Rated value  — at 110 V Rated value  — at 24 V Rated value  — at 250 V Rated value  — at 260 V Rated value  — at 270 V Rated value  — at 270 V Rated value  — a	Operating current		
Rated value — up to 690 V at ambient temperature 40 °C Rated value — up to 690 V at ambient temperature 60 °C Rated value — up to 690 V at ambient temperature 60 °C Rated value • at AC-2 at 400 V Rated value • at AC-3 — at 400 V Rated value — at 590 V Rated value — at 590 V Rated value — at 590 V Rated value — at 690 V Rated value — at 400 V Rated value — at 24 V Rated value — at 110 V Rated value — at 110 V Rated value — at 440 V Rated value — at 220 V Rated value — at 24 V Rated value — at 600 V Rated value — at 600 V Rated value — at 10 V Rated value — at 10 V Rated value — at 10 V Rated value — at 110 V Rated value — at 220 V Rated	• at AC-1		
Rated value  — up to 690 V at ambient temperature 60 °C Rated value  • at AC-2 at 400 V Rated value  • at AC-3  — at 400 V Rated value — at 500 V Rated value  • at AC-4 at 400 V Rated value — at 500 V Rated value  • at AC-4 at 400 V Rated value  • at DC-1  — at 24 V Rated value — at 110 V Rated value — at 220 V Rated value — at 600 V Rated value — at 700 V Rated value — at 700 V Rated value — at 700 V Rated value — at 110 V Rated value — at 220 V Rated value — at 24 V Rated value — at 220 V Rated value		А	22
Rated value       ● at AC-2 at 400 V Rated value       A       9         • at AC-3       — at 400 V Rated value       A       9         — at 500 V Rated value       A       7.7         — at 690 V Rated value       A       6.7         • at AC-4 at 400 V Rated value       A       8.5         Operating current with 1 current path       • at DC-1         — at 24 V Rated value       A       20         — at 110 V Rated value       A       2.1         — at 220 V Rated value       A       0.8         — at 440 V Rated value       A       0.6         • at DC-3 at DC-5       — at 24 V Rated value       A       0.1         • at DC-3 at DC-5       — at 24 V Rated value       A       0.1         — at 110 V Rated value       A       20         — at 110 V Rated value       A       1.6         — at 220 V Rated value       A       1.6         — at 24 V Rated value       A       0.7         • at DC-3 at DC-5       — at 110 V Rated value       A       0.35         — at 110 V Rated value       A       0.35         — at 24 V Rated value       A       20         Operating current with 3 current paths in series       • at DC-1 <td></td> <td>Α</td> <td>22</td>		Α	22
• at AC-3  — at 400 V Rated value — at 500 V Rated value — at 690 V Rated value A 7.7  — at 690 V Rated value A 6.7  • at AC-4 at 400 V Rated value A 8.5  Operating current with 1 current path • at DC-1 — at 24 V Rated value — at 110 V Rated value A 0.8 — at 440 V Rated value A 0.6 — at 440 V Rated value A 0.6 — at 600 V Rated value A 0.6 • at DC-3 — at 24 V Rated value A 0.6  • at DC-3 v Rated value A 0.6  • at DC-3 v Rated value A 0.1  Operating current with 2 current paths in series • at DC-1 — at 24 V Rated value A 1.6 — at 440 V Rated value A 1.6 — at 440 V Rated value A 0.8 — at 600 V Rated value A 1.6 — at 440 V Rated value A 1.6 — at 24 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  • at DC-1 — at 24 V Rated value A 0.7  A 0.8  A 0.9		Α	20
- at 400 ∨ Rated value	• at AC-2 at 400 V Rated value	Α	9
— at 500 ∨ Rated value	• at AC-3		
— at 690 ∨ Rated value A 8.5  Operating current with 1 current path  ■ at DC-1  — at 24 ∨ Rated value A 2.1  — at 110 ∨ Rated value A 0.6  — at 440 ∨ Rated value A 0.6  — at 440 ∨ Rated value A 0.6  — at 50 ∨ Rated value A 0.6  — at 10C-3 at DC-5  — at 24 ∨ Rated value A 0.1  Operating current with 2 current paths in series  ■ at DC-1  — at 24 ∨ Rated value A 0.1  Operating current with 2 current paths in series  ■ at DC-1  — at 24 ∨ Rated value A 1.6  — at 440 ∨ Rated value A 1.6  — at 110 ∨ Rated value A 1.6  — at 220 ∨ Rated value A 0.8  — at 210 ∨ Rated value A 1.6  — at 440 ∨ Rated value A 0.8  — at 220 ∨ Rated value A 0.7  ■ at DC-3 at DC-5  — at 110 ∨ Rated value A 0.8  — at 24 ∨ Rated value A 0.8  — at 24 ∨ Rated value A 0.7  ■ at DC-3 at DC-5  — at 110 ∨ Rated value A 0.35  — at 24 ∨ Rated value A 0.35  — at 24 ∨ Rated value A 20  Operating current with 3 current paths in series  ■ at DC-1  — at 24 ∨ Rated value A 20  — at 24 ∨ Rated value A 20  — at 22 ∨ Rated value A 20  — at 24 ∨ Rated value A 20  — at 22 ∨ Rated value A 20  — at 24 ∨ Rated value A 20  — at 25 ∨ Rated value A 20  — at 26 ∨ Ra	— at 400 V Rated value	Α	9
■ at AC-4 at 400 V Rated value     Operating current with 1 current path     ■ at DC-1     — at 24 V Rated value     — at 110 V Rated value     — at 440 V Rated value     — at 440 V Rated value     — at 600 V Rated value     — at 600 V Rated value     — at 100 V Rated value     — at 100 V Rated value     — at 24 V Rated value     — at 110 V Rated value     — at 220 V Rated value     — at 110 V Rated value     — at 20 V Rated value     — at 20 V Rated value     — at 440 V Rated value     — at 440 V Rated value     — at 40 V Rated value     — at 40 V Rated value     — at 220 V Rated value     — at 24 V Rated value     — at 220 V Rated value     — at 440 V Rated value     — at 220 V Rated value     — at 440 V Rated value	— at 500 V Rated value	Α	7.7
Operating current with 1 current path              ■ at DC-1          A 20          2.1          A 2.1          A 2.1          A 0.8          A 0.8          A 0.8          A 0.6          A 0.7          A 0.1         Operating current with 2 current paths in series          A 0.1         Operating current with 2 current paths in series          A 12          A 1.6          A 1.6          A 0.8          A 1.6          A 0.7          A 1.6          A 0.7          A 1.10          A 1.0          A 0.7	— at 690 V Rated value	Α	6.7
• at DC-1  — at 24 V Rated value — at 110 V Rated value A 2.1  — at 220 V Rated value A 0.8  — at 440 V Rated value A 0.6  — at 600 V Rated value A 0.6  • at DC-3 at DC-5  — at 24 V Rated value A 0.1  Operating current with 2 current paths in series  • at DC-1  — at 220 V Rated value A 1.6  — at 440 V Rated value A 0.8  — at 400 V Rated value A 0.8  — at 20  — at 110 V Rated value A 1.6  — at 440 V Rated value A 0.7  • at DC-3 at DC-5  — at 100 V Rated value A 0.8  — at 20 V Rated value A 0.8  — at 20 V Rated value A 0.8  — at 20 V Rated value A 0.7  • at DC-3 at DC-5  — at 110 V Rated value A 0.35  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  — at 20 V Rated value A 20  — at 20 V Rated value A 20  — at 440 V Rated value A 20	• at AC-4 at 400 V Rated value	Α	8.5
• at DC-1  — at 24 V Rated value — at 110 V Rated value A 2.1  — at 220 V Rated value A 0.8  — at 440 V Rated value A 0.6  — at 600 V Rated value A 0.6  • at DC-3 at DC-5  — at 24 V Rated value A 0.1  Operating current with 2 current paths in series  • at DC-1  — at 220 V Rated value A 1.6  — at 440 V Rated value A 0.8  — at 400 V Rated value A 0.8  — at 20  — at 110 V Rated value A 1.6  — at 440 V Rated value A 0.7  • at DC-3 at DC-5  — at 100 V Rated value A 0.8  — at 20 V Rated value A 0.8  — at 20 V Rated value A 0.8  — at 20 V Rated value A 0.7  • at DC-3 at DC-5  — at 110 V Rated value A 0.35  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A 20  — at 20 V Rated value A 20  — at 20 V Rated value A 20  — at 440 V Rated value A 20	Operating current with 1 current path		
— at 220 V Rated value — at 440 V Rated value A 0.6 — at 600 V Rated value A 0.6  • at DC-3 at DC-5 — at 24 V Rated value A 0.1  Operating current with 2 current paths in series • at DC-1 — at 24 V Rated value A 1.6 — at 110 V Rated value A 1.6 — at 440 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 1.6 — at 440 V Rated value A 0.8 — at 600 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.35 — at 24 V Rated value A 20  Operating current with 3 current paths in series • at DC-1 — at 24 V Rated value A 20  Operating current with 3 current paths in series • at DC-1 — at 24 V Rated value A 20 — at 110 V Rated value A 20 — at 20 V Rated value A 20 — at 20 V Rated value A 20 — at 20 V Rated value A 20 — at 440 V Rated value A 20	— at 24 V Rated value	Α	20
— at 440 V Rated value — at 600 V Rated value  • at DC-3 at DC-5 — at 24 V Rated value A 0.1  Operating current with 2 current paths in series  • at DC-1 — at 24 V Rated value A 12 — at 110 V Rated value A 12 — at 110 V Rated value A 12 — at 220 V Rated value A 1.6 — at 440 V Rated value A 0.8 — at 600 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.7  • at DC-3 at DC-5 — at 110 V Rated value A 0.35 — at 24 V Rated value A 0.35 — at 24 V Rated value A 20  Operating current with 3 current paths in series  • at DC-1 — at 24 V Rated value A 20 — at 20 V Rated value A 20 — at 440 V Rated value A 1.3	— at 110 V Rated value	Α	2.1
- at 600 V Rated value  • at DC-3 at DC-5  — at 24 V Rated value A  — at 110 V Rated value A  Operating current with 2 current paths in series  • at DC-1  — at 24 V Rated value A  — at 110 V Rated value A  — at 110 V Rated value A  — at 220 V Rated value A  — at 440 V Rated value A  — at 600 V Rated value A  • at DC-3  • at DC-5  — at 110 V Rated value A  — at 24 V Rated value A  • at DC-3 at DC-5  — at 110 V Rated value A  — at 24 V Rated value A  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A  — at 20  Operating current with 3 current paths in series  • at DC-1  — at 24 V Rated value A  — at 20  — at 20 V Rated value A  — at 110 V Rated value A  — at 20  — at 20 V Rated value A  — at 110 V Rated value A  — at 20 V Rated value A  — at 20 V Rated value A  — at 20 V Rated value A  — at 440 V Rated value A  — at 20 V Rated value A  — at 440 V Rated value A  — at 1.3	— at 220 V Rated value	Α	0.8
at DC-3 at DC-5     — at 24 V Rated value     — at 110 V Rated value     A     Derating current with 2 current paths in series     at DC-1     — at 24 V Rated value     — at 110 V Rated value     — at 220 V Rated value     — at 440 V Rated value     — at 600 V Rated value     — at 110 V Rated value     A     A     A     D.7      at DC-3 at DC-5     — at 110 V Rated value     A     A     O.7      at DC-3 at DC-5     — at 24 V Rated value     A     A     D.35     — at 24 V Rated value     A     A     Doperating current with 3 current paths in series     at DC-1     — at 24 V Rated value     A     A     Derating current with 3 current paths in series     at DC-1     — at 24 V Rated value     — at 24 V Rated value     — at 24 V Rated value     A     A     20     — at 110 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     A     20     — at 440 V Rated value     A     30     A     30     A     30	— at 440 V Rated value	Α	0.6
at 24 V Rated value at 110 V Rated value A 0.1  Operating current with 2 current paths in series  ■ at DC-1  at 24 V Rated value A 12  at 220 V Rated value A 1.6  at 440 V Rated value A 0.8  at 600 V Rated value A 0.7  ■ at DC-3 at DC-5  at 110 V Rated value A 0.35  at 24 V Rated value A 0.0  Operating current with 3 current paths in series ■ at DC-1  at 24 V Rated value A 20  Operating current with 3 current paths in series ■ at DC-1  at 24 V Rated value A 20  at 110 V Rated value A 20  at 110 V Rated value A 20  at 220 V Rated value A 20  at 440 V Rated value A 3 3	— at 600 V Rated value	Α	0.6
— at 110 V Rated value A 0.1  Operating current with 2 current paths in series  ● at DC-1  — at 24 V Rated value A 12 — at 220 V Rated value A 1.6 — at 440 V Rated value A 0.8 — at 600 V Rated value A 0.7  ● at DC-3 at DC-5 — at 110 V Rated value A 0.35 — at 24 V Rated value A 20  Operating current with 3 current paths in series  ● at DC-1 — at 24 V Rated value A 20  — at 110 V Rated value A 20 — at 110 V Rated value A 20 — at 110 V Rated value A 20 — at 220 V Rated value A 20 — at 440 V Rated value A 1.3	• at DC-3 at DC-5		
Operating current with 2 current paths in series         ● at DC-1         — at 24 V Rated value       A       20         — at 110 V Rated value       A       12         — at 220 V Rated value       A       1.6         — at 440 V Rated value       A       0.8         — at 600 V Rated value       A       0.7         ● at DC-3 at DC-5       — at 110 V Rated value       A       20         Operating current with 3 current paths in series       ● at DC-1       — at 24 V Rated value       A       20         — at 110 V Rated value       A       20         — at 220 V Rated value       A       20         — at 440 V Rated value       A       20	— at 24 V Rated value	Α	20
■ at DC-1     — at 24 V Rated value     — at 110 V Rated value     — at 220 V Rated value     — at 440 V Rated value     — at 600 V Rated value     — at 600 V Rated value     — at 110 V Rated value     — at 110 V Rated value     — at 24 V Rated value     — at 440 V Rated value	— at 110 V Rated value	Α	0.1
- at 24 V Rated value     - at 110 V Rated value     - at 220 V Rated value     - at 440 V Rated value     - at 600 V Rated value     - at 100 V Rated value     - at 100 V Rated value     - at 110 V Rated value     - at 24 V Rated value     - at 250 V Rated value     - at 250 V Rated value     - at 350 V Rated value	Operating current with 2 current paths in series		
- at 110 V Rated value     - at 220 V Rated value     - at 440 V Rated value     - at 600 V Rated value     - at 110 V Rated value     - at 600 V Rated value     - at 110 V Rated value     - at 110 V Rated value     - at 24 V Rated value     - at 320 V Rated value     - at 440 V Rated value	• at DC-1		
- at 220 V Rated value A A D.8 A 0.8 A 0.7  ■ at DC-3 at DC-5 A at 110 V Rated value A A D.7  ■ at 24 V Rated value A A DOperating current with 3 current paths in series  ■ at DC-1 A A DC-1 A DC-1 A	— at 24 V Rated value	Α	20
<ul> <li>— at 440 V Rated value</li> <li>— at 600 V Rated value</li> <li>A 0.7</li> <li>● at DC-3 at DC-5</li> <li>— at 110 V Rated value</li> <li>— at 24 V Rated value</li> <li>A 20</li> <li>Operating current with 3 current paths in series</li> <li>● at DC-1</li> <li>— at 24 V Rated value</li> <li>— at 110 V Rated value</li> <li>— at 110 V Rated value</li> <li>— at 220 V Rated value</li> <li>— at 220 V Rated value</li> <li>— at 440 V Rated value</li> <li>A 20</li> <li>— at 440 V Rated value</li> <li>A 1.3</li> </ul>	— at 110 V Rated value	Α	12
<ul> <li>— at 600 V Rated value</li> <li>● at DC-3 at DC-5</li> <li>— at 110 V Rated value</li> <li>— at 24 V Rated value</li> <li>A 20</li> <li>Operating current with 3 current paths in series</li> <li>● at DC-1</li> <li>— at 24 V Rated value</li> <li>— at 110 V Rated value</li> <li>— at 110 V Rated value</li> <li>— at 220 V Rated value</li> <li>— at 440 V Rated value</li> <li>A 20</li> <li>— at 440 V Rated value</li> <li>A 1.3</li> </ul>	— at 220 V Rated value	Α	1.6
■ at DC-3 at DC-5     — at 110 V Rated value     A 0.35     — at 24 V Rated value     A 20  Operating current with 3 current paths in series     ■ at DC-1     — at 24 V Rated value     A 20     — at 110 V Rated value     A 20     — at 110 V Rated value     A 20     — at 440 V Rated value     A 1.3	— at 440 V Rated value	Α	0.8
— at 110 V Rated value       A       0.35         — at 24 V Rated value       A       20         Operating current with 3 current paths in series         • at DC-1       —         — at 24 V Rated value       A       20         — at 110 V Rated value       A       20         — at 220 V Rated value       A       20         — at 440 V Rated value       A       1.3	— at 600 V Rated value	Α	0.7
<ul> <li>— at 24 V Rated value</li> <li>A 20</li> <li>Operating current with 3 current paths in series</li> <li>• at DC-1</li> <li>— at 24 V Rated value</li> <li>— at 110 V Rated value</li> <li>— at 220 V Rated value</li> <li>— at 220 V Rated value</li> <li>— at 440 V Rated value</li> <li>A 1.3</li> </ul>	• at DC-3 at DC-5		
Operating current with 3 current paths in series   • at DC-1  — at 24 V Rated value  — at 110 V Rated value  A 20  — at 220 V Rated value  A 20  — at 440 V Rated value  A 1.3	— at 110 V Rated value	Α	0.35
<ul> <li>at DC-1         <ul> <li>at 24 V Rated value</li> <li>at 110 V Rated value</li> <li>at 220 V Rated value</li> <li>at 440 V Rated value</li> </ul> </li> <li>A 20</li> <li>A 20</li> <li>A 1.3</li> </ul>	— at 24 V Rated value	Α	20
— at 24 V Rated value       A       20         — at 110 V Rated value       A       20         — at 220 V Rated value       A       20         — at 440 V Rated value       A       1.3	Operating current with 3 current paths in series		
— at 110 V Rated value       A       20         — at 220 V Rated value       A       20         — at 440 V Rated value       A       1.3	• at DC-1		
<ul> <li>— at 220 V Rated value</li> <li>— at 440 V Rated value</li> <li>A 1.3</li> </ul>	— at 24 V Rated value	Α	20
— at 440 V Rated value A 1.3	— at 110 V Rated value	Α	20
	— at 220 V Rated value	Α	20
— at 600 V Rated value A 1	— at 440 V Rated value	Α	1.3
	— at 600 V Rated value	Α	1

• at DC-3 at DC-5		
— at 110 V Rated value	Α	20
— at 220 V Rated value	Α	1.5
— at 24 V Rated value	Α	20
— at 440 V Rated value	Α	0.2
— at 600 V Rated value	Α	0.2
Operating power		
• at AC-1 at 400 V Rated value	kW	13
• at AC-2 at 400 V Rated value	kW	4
• at AC-4 at 400 V Rated value	kW	4
Operating power		
• at AC-1		
— at 230 V at 60 °C Rated value	kW	7.5
— at 230 V Rated value	kW	7.5
— at 400 V at 60 °C Rated value	kW	13
— at 690 V at 60 °C Rated value	kW	22
— at 690 V Rated value	kW	22
• at AC-3		
— at 230 V Rated value	kW	2.2
— at 400 V Rated value	kW	4
— at 690 V Rated value	kW	5.5
Operating power for ≥ 200000 operating cycles at AC-4		
• at 400 V Rated value	kW	2
• at 690 V Rated value	kW	2.5
Operating frequency		
• at AC-3 maximum	1/h	750
Control circuit/ Control:		
Type of voltage of the control supply voltage		AC
Control supply voltage with AC		
● at 50 Hz Rated value	V	100
• at 60 Hz Rated value	V	110
Operating range factor control supply voltage rated		
value of the magnet coil with AC		0.8 1.1
• at 50 Hz		
● at 60 Hz		0.85 1.1
Auxiliary circuit:		
Number of NC contacts		
• for auxiliary contacts		
— instantaneous contact		1
Number of NO contacts		

for auxiliary contacts		
— instantaneous contact		0
Product expansion Auxiliary switch		Yes
Operating current at AC-15		
• at 230 V Rated value	Α	10
● at 400 V Rated value	Α	3
● at 690 V Rated value	Α	1
Operating current		
● at DC-12 at 125 V Rated value	Α	2
• at DC-12 at 220 V Rated value	Α	1
● at DC-12 at 600 V Rated value	Α	0.15
• at DC-13 at 125 V Rated value	Α	0.9
• at DC-13 at 220 V Rated value	Α	0.3
• at DC-13 at 600 V Rated value	Α	0.1
Operating current		
• at DC-12		
— at 60 V Rated value	Α	6
— at 110 V Rated value	Α	3
• at DC-13		
— at 24 V Rated value	Α	10
— at 60 V Rated value	Α	2
— at 110 V Rated value	Α	1
Contact reliability of the auxiliary contacts		1 faulty switching per 100 million (17 V, 1 mA)
JL/CSA ratings:		
Full-load current (FLA) for three-phase AC motor		
• at 480 V Rated value	Α	7.6
• at 600 V Rated value	Α	9
yielded mechanical performance [hp]		
● for single-phase AC motor at 110/120 V Rated value	metric hp	0.33
• for single phase AC mater at 220 \/ Dated	motric	1

oz/oo/trainigo.		
Full-load current (FLA) for three-phase AC motor		
● at 480 V Rated value	Α	7.6
● at 600 V Rated value	Α	9
yielded mechanical performance [hp]		
<ul> <li>• for single-phase AC motor at 110/120 V Rated value</li> </ul>	metric hp	0.33
<ul> <li>for single-phase AC motor at 230 V Rated value</li> </ul>	metric hp	1
● for three-phase AC motor at 200/208 V Rated value	metric hp	2
<ul> <li>for three-phase AC motor at 220/230 V Rated value</li> </ul>	metric hp	3
<ul> <li>for three-phase AC motor at 460/480 V Rated value</li> </ul>	metric hp	5
● for three-phase AC motor at 575/600 V Rated value	metric hp	7.5
Contact rating of the auxiliary contacts acc. to UL		A600 / Q600

# Short-circuit:

# Design of the fuse link

- for short-circuit protection of the main circuit
  - with type of assignment 1 required
  - with type of assignment 2 required
- for short-circuit protection of the auxiliary switch required

gL/gG LV HRC 3NA, DIAZED 5SB, NEOZED 5SE: 35 A

gL/gG LV HRC 3NA, DIAZED 5SB, NEOZED 5SE: 20 A

fuse gL/gG: 10 A

mounting position		+/-180° rotation possible on vertical mounting
		surface; can be tilted forward and backward by +/-
		22.5° on vertical mounting surface
Mounting type		screw and snap-on mounting onto 35 mm standard
		mounting rail according to DIN EN 50022
Side-by-side mounting		Yes
Height	mm	57.5
Width	mm	45
Depth	mm	73
Required spacing		
<ul><li>with side-by-side mounting</li></ul>		
— forwards	mm	0
— Backwards	mm	0
— upwards	mm	0
— downwards	mm	0
— at the side	mm	0
• for grounded parts		
— forwards	mm	0
— Backwards	mm	0
— upwards	mm	0
— at the side	mm	6
— downwards	mm	0
• for live parts		
— forwards	mm	0
— Backwards	mm	0
— upwards	mm	0
— downwards	mm	0
— at the side	mm	6

#### for main current circuit

Type of electrical connection

for auxiliary and control current circuit

Apparent pick-up power of the magnet coil with AC

ring cable connection ring cable connection

● at 50 Hz	V·A	27
● at 60 Hz	V·A	24.3

	1 000 000
%	40
%	73
FIT	100
	Yes
у	20
	finger-safe
	S00
m	2 000
°C	-25 <b>+</b> 60
	% FIT y

#### **General Product Approval**

Functional Safety/Safety of Machinery Declaration of Conformity









Type Examination



ı	е	St			
	_			ı	

# **Shipping Approval**

#### Certificates

Special Test Certificate













LRS

# **Shipping Approval**

#### other







Environmental Confirmations

Confirmation



# Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system)

http://www.siemens.com/industrymall

#### Cax online generator

 $\underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx.lang=en\&mlfb=3RT20164AG62} \\ \underline{\text{http://support.automatio$ 

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

http://support.automation.siemens.com/WW/view/en/3RT20164AG62/all

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RT20164AG62&lang=en



