

**Features**

- 2-channel
- DC version, positive polarity
- Working voltage 26.5 V at 10  $\mu$ A
- Series resistance max. 327  $\Omega$
- Fuse rating 50 mA
- DIN rail mounting
- With diode return

**Function**


The Zener Barrier prevents the transfer of unacceptably high energy from the safe area into the hazardous area.

The zener diodes in the Zener Barrier are connected in the reverse direction. The breakdown voltage of the diodes is not exceeded in normal operation. If this voltage is exceeded, due to a fault in the safe area, the diodes start to conduct, causing the fuse to blow. The Zener Barrier has a positive polarity, i. e. the anodes of the zener diodes are grounded.



The Zener Barrier is for evaluation of signals from the hazardous area. The diodes of diode return prevent a current into the hazardous area, therefore the current assumption for intrinsic safety calculations is zero.

Depending on the application, increased or decreased intrinsic safety parameters apply for serial or parallel connection. For the detailed parameters refer to the Zener Barrier certificate. Application examples can be found in the system description of the Zener Barriers.

**Assembly**



**Connection**



**Zone 2**  
**Div. 2**

Release date 2016-05-18 14:16 Date of issue 2016-05-18 071816\_eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group  
www.pepperl-fuchs.com

USA: +1 330 486 0002  
pa-info@us.pepperl-fuchs.com

Germany: +49 621 776 2222  
pa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091  
pa-info@sg.pepperl-fuchs.com

<b>General specifications</b>		
Type		DC version, positive polarity
<b>Electrical specifications</b>		
Nominal resistance		300 Ω
Series resistance		terminals 1 and 8 : max. 327 Ω
Voltage drop		terminals 4 and 5 : 1.2 V + (36 Ω x signal current)
Fuse rating		50 mA
<b>Hazardous area connection</b>		
Connection		terminals 1, 2; 3, 4
<b>Safe area connection</b>		
Connection		terminals 5, 6; 7, 8
Working voltage		max. 27 V , 26.5 V at 10 μA
<b>Conformity</b>		
Degree of protection		IEC 60529
<b>Ambient conditions</b>		
Ambient temperature		-20 ... 60 °C (-4 ... 140 °F)
Storage temperature		-25 ... 70 °C (-13 ... 158 °F)
Relative humidity		max. 75 % , without moisture condensation
<b>Mechanical specifications</b>		
Degree of protection		IP20
Connection		screw terminals , max. core cross-section 2 x 2.5 mm <sup>2</sup>
Mass		approx. 150 g
Dimensions		12.5 x 115 x 110 mm (0.5 x 4.5 x 4.3 in)
Construction type		modular terminal housing , see system description
Mounting		on 35 mm DIN mounting rail acc. to EN 60715:2001
<b>Data for application in connection with Ex-areas</b>		
EC-Type Examination Certificate		BAS 01 ATEX 7005
Group, category, type of protection		⊕ II (1)GD, I (M1) [Ex ia Ga] IIC, [Ex ia Da] IIIC, [Ex ia Ma] I (-20 °C ≤ T <sub>amb</sub> ≤ 60 °C) [circuit(s) in zone 0/1/2]
Voltage U <sub>o</sub>		28 V
Current I <sub>o</sub>		93 mA
Power P <sub>o</sub>		650 mW
Supply		
Maximum safe voltage U <sub>m</sub>		250 V
Series resistance		min. 301 Ω
Statement of conformity		TÜV 99 ATEX 1484 X
Group, category, type of protection, temperature class		⊕ II 3G Ex nA IIC T4 Gc [device in zone 2]
Directive conformity		
Directive 2014/34/EU		EN 60079-0:2012+A11:2013 , EN 60079-11:2012 , EN 60079-15:2010
<b>International approvals</b>		
FM approval		
Control drawing		116-0118
UL approval		
Control drawing		116-0139
CSA approval		
Control drawing		116-0119
IECEx approval		IECEx BAS 09.0142
Approved for		[Ex ia Ga] IIC, [Ex ia Da] IIIC, [Ex ia Ma] I
<b>General information</b>		
Supplementary information		EC-Type Examination Certificate, Statement of Conformity, Declaration of Conformity, Attestation of Conformity and instructions have to be observed where applicable. For information see <a href="http://www.pepperl-fuchs.com">www.pepperl-fuchs.com</a> .

Release date 2016-05-18 14:16 Date of issue 2016-05-18 07:18:16\_eng.xml