
## **SIEMENS**

## **Data sheet**

## 6ES7870-1AB01-0YA0



SIMATIC S7, MODBUS Slave V3.1 single license for 1 installation R-SW, SW and DOCU on CD, HW dongle, Class A, 3 languages (de, de, fr, en fr), executable in STEP 7 V4.02 or higher, reference hardware: CP 341 and CP 441-2

| Operating systems  |   |
|--|---|
| Runs under operating system  |   |
| <ul><li>Windows 9x</li></ul>   | No  |
| <ul> <li>Windows ME</li> </ul>   | No  |
| <ul><li>Windows NT 4.0</li></ul>   | No  |
| <ul><li>Windows 2000</li></ul>   | No  |
| <ul> <li>Windows XP</li> </ul>   | Yes   |
| Software   |   |
| Software class   | A   |
| Target system  | CP 341 AND CP 441-2                               |
| Block  |   |
| <ul> <li>Communications FB instance DB</li> </ul>  | FB 180, DB 180 (use of a multi-instance)          |
| Adjustable parameters  |   |
| <ul> <li>Enable of the memory areas writeable by the master possible</li> </ul>                      | Yes   |
| <ul> <li>Number of work DB (for FB editing) possible</li> </ul>                                      | Yes   |
| <ul> <li>Factor for the character delay time</li> </ul>  | 1 to 10   |
| <ul> <li>Modem operation (ignore filler characters)</li> </ul>                                       | with/without                                      |
| <ul> <li>RS 485 operation for 2-wire connection</li> </ul>   | with/without                                      |
| <ul> <li>Slave address of the CP</li> </ul>  | <u>1 to 255</u>                                   |
| Transmission rate  | 300 bit/s to 76 800 bit/s; (TTY to 19 200 bit/s)  |
| <ul> <li>Conversion of Modbus addresses to S7 data areas</li> </ul>                                  | Yes   |
| <ul> <li>Preassignment of receive circuit on application of the<br/>X.27 interface module</li> </ul> | Yes   |
| Character frame  | Yes   |
| Communication data   |   |
| <ul> <li>CRC polynomial</li> </ul>   | X16 + x15 + x2 + 1                                |
| <ul> <li>Modbus protocol</li> </ul>  | with RTU format                                   |
| <ul> <li>implemented function codes</li> </ul>   | 01, 02, 03, 04, 05, 06, 08, 15, 16                |
| <ul> <li>Conversion of Modbus addresses to S7 data areas</li> </ul>                                  | DB, memory bits, outputs, inputs, times, counters |
| <ul> <li>V.24 control and signal cables</li> </ul>   | none  |
| Character delay time   | 3.5 characters or multiples                       |
| Authorization/licenses   |   |
| <ul> <li>Single license (EL)</li> </ul>  | Yes   |
| configuration / header   |   |
| configuration / programming / header   |   |
| Programming language   |   |
| — LAD  | Yes   |
| — FBD  | Yes   |
| — STL  | Yes   |

| Documentation |     |
|---------------|-----|
| Languages     |     |
| German        | Yes |
| English       | Yes |
| • French      | Yes |

last modified: 3/4/2021 🖸