SIEMENS

Data sheet

3RW40 36-1BB14

SIRIUS SOFT STARTER, S2, 45A, 22KW/400V, 40 DEGR., AC 200-480V, AC/DC 110-230V, SCREW

TERMINALS



Figure similar


General technical data:				
product brand name	SIRIUS			
Product feature				
 integrated bypass contact system 	Yes			
Thyristors	Yes			
Product function				
 Intrinsic device protection 	Yes			
 motor overload protection 	Yes			
 Evaluation of thermistor motor protection 	No			
External reset	Yes			
 Adjustable current limitation 	Yes			
• inside-delta circuit	No			
Product component Motor brake output	No			
Equipment marking acc. to DIN EN 61346-2	Q			
Equipment marking acc. to DIN 40719 extended according to IEC 204-2 acc. to IEC 750	G			

	soft starters for standard applications
А	45
А	42
А	39
	A

at standard size it at 40 % Data devalue	W	11 000
— at standard circuit at 40 °C Rated value	VV	11000
• at 400 V		
— at standard circuit at 40 °C Rated value	W	22 000
yielded mechanical performance [hp] for three-phase	metric	10
AC motor at 200/208 V at standard circuit at 50 °C	hp	
Rated value		
Operating frequency Rated value	Hz	50 60
Relative negative tolerance of the operating frequency	%	-10
Relative positive tolerance of the operating frequency	%	10
Operating voltage at standard circuit Rated value	V	200 480
Relative negative tolerance of the operating voltage at standard circuit	%	-15
Relative positive tolerance of the operating voltage at standard circuit	%	10
Minimum load in % of I_M	%	20
Adjustable motor current for motor overload protection minimum rated value	A	23
Continuous operating current in % of I_e at 40 °C	%	115
Active power loss at operating current at 40 °C during operation typical	W	6
Control electronics:		
Type of voltage of the control supply voltage		AC/DC
Control supply voltage frequency 1 Rated value	Hz	50
Control supply voltage frequency 1 Rated value Control supply voltage frequency 2 Rated value	Hz Hz	50 60
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply	Hz	60
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply	Hz %	60 -10
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency	Hz %	60 -10 10
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz	Hz % % V	60 -10 10 110 230
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply	Hz % % V V	60 -10 10 110 230 110 230
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply	Hz % % V V %	60 -10 10 110 230 110 230 -15
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz	Hz % % V V %	60 -10 10 110 230 110 230 -15 10
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply	Hz % % V V % %	60 -10 10 110 230 110 230 -15 10 110 230
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC	Hz % V V % % V	60 -10 10 110 230 110 230 -15 10 110 230 -15
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC	Hz % V V % % V	60 -10 10 110 230 110 230 -15 10 110 230 -15 10
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC	Hz % V V % % V	60 -10 10 110 230 110 230 -15 10 110 230 -15 10
Control supply voltage frequency 2 Rated value Relative negative tolerance of the control supply voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal Mechanical data:	Hz % V V % % V	60 -10 10 110 230 110 230 -15 10 110 230 -15 10 red

Height	mm	160
Depth	mm	170
Mounting type	-	screw and snap-on mounting
mounting position		With additional fan: With vertical mounting surface +/- 90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back Without additional fan: With vertical mounting surface +/-10° rotatable, with vertical mounting surface +/- 10° t
Required spacing with side-by-side mounting	_	
• upwards	mm	60
• at the side	mm	30
• downwards	mm	40
Installation altitude at height above sea level	m	5 000
Cable length maximum	m	300
Number of poles for main current circuit	_	3
Connections/ Terminals:		
Type of electrical connection		
 for main current circuit 		screw-type terminals
 for auxiliary and control current circuit 		screw-type terminals
Number of NC contacts for auxiliary contacts		0
Number of NO contacts for auxiliary contacts	-	2
Number of CO contacts for auxiliary contacts	_	1
Type of connectable conductor cross-section for main contacts for box terminal using the front clamping point	-	
• solid		2x (1.5 16 mm²)
 finely stranded with core end processing 		0.75 25 mm²
• stranded		0.75 35 mm²
Type of connectable conductor cross-section for main contacts for box terminal using the back clamping point	_	
• solid		2x (1.5 16 mm²)
 finely stranded with core end processing 		1.5 25 mm²
• stranded		1.5 35 mm²
Type of connectable conductor cross-section for main contacts for box terminal using both clamping points		
• solid		2x (1.5 16 mm²)
 finely stranded with core end processing 		2x (1.5 16 mm²)
• stranded		2x (1.5 25 mm²)
Type of connectable conductor cross-section for		
AWG conductors for main contacts for box terminal		
 using the back clamping point 		16 2
 using the front clamping point 		18 2

	nping points			2x (16 2)			
	conductor cross-see	ction for					
uxiliary contacts							
 solid finely stranded with core end processing Type of connectable conductor cross-section for AWG conductors for auxiliary contacts 				2x (0.5 2.5 mm²)			
				2x (0.5 1.5	1.5 mm²)		
				2x (20 14)	2x (20 14)		
 for auxiliary contacts finely stranded with core end processing 				2x (20 16)			
nbient conditions:							
mbient temperature	•						
 during operatio 	on		°C	-25 +60			
• during storage		°C	-40 +80				
erating temperature	9		°C	40			
rotection class IP			_	IP00			
ertificates/ approva					EMC	Foruga in	
ertificates/ approva General Product					EMC	For use in hazardous locations	
			E	AC	EMC C-TICK	hazardous	
General Product	t Approval	UL Shipping /		AC	C	hazardous locations	
General Product	t Approval		Approval		C	hazardous locations	
General Product	t Approval	Shipping /	Approval	GL®	C-TICK	hazardous locations	



— at standard circuit at 50 °C Rated value	metric hp	15
● at 460/480 V		
— at standard circuit at 50 °C Rated value	metric	30
	hp	
Contact rating of the auxiliary contacts acc. to UL		B300 / R300

urther information

Information- and Downloadcenter (Catalogs, Brochures,...) http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system) http://www.siemens.com/industrymall

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RW40361BB14

Service&Support (Manuals, Certificates, Characteristics, FAQs,...) http://support.automation.siemens.com/WW/view/en/3RW40361BB14/all

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/index.aspx?attID9=3RW40361BB14&lang=en

