PT 7,5/2/6



Advantages

Minimum size at high output

Integrated overload protection using PTC in the input

Also with dual output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDenseFill resin encapsulation

Self-extinguishing potting material


Space saving installation thanks to additional screw mounting in the base

Applications

As a mains transformer for adjustment of the voltage and simple electrical

Safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6 Approvals







VDE, UL 5085-1/-2, CSA 22.2 No.66





Safety isolating transformer **PT 7,5/2/6**

	Туре	PT 7,5/2/6		Туре	PT 7,5/2/6
Electrical data +	Input		0	l ype Terminal and mounting Terminals	
	Rated input voltage	230 Vac	۳.	Terminals	Pins for PCB
	Rated frequency	50 - 60 Hz		Measures and weights	
	Output		data	Pin (ø)	0.8 mm
	Rated output voltage	2 x 6 Vac	9	Core type	EI 48/16,8
	Rated Power	7.5 VA	<u></u>	Weight	0.28 kg
	No-load voltage (app. x factor)	1.21	.은		
	No-load loss (typ.)	1.30 W	Mechanical		
	Efficiency	65.0 %	9		
	Standards		Š		
	Classification	Safety isolating transformer			
	Approvals				15.0
	Approvals	cURus, VDE		40.0 51.0 36.0 7.0	
	Environment				
	Ambient temperature max.	40 °C			
	Safety and protection				
	Туре	Encapsulated		43.0	
	Insulation class	VDE=E, UL=class 105			
	Protection index	IP 00			
	Safety class (prepared)	II			
	Short circuit strength	non-inherently short-circuit proof			
	Order numbers				
	Order Number	PT 7,5/2/6			

