

VMA120D 120W 100V 1U Mixer Amplifier

The VMA120D is a 1U 19" rack-mountable 5 channel mixer with a built-in media player and 120W Class-D mono amplifier for driving either 100V or low impedance speakers. With its array of connectivity and playback options the VMA120D is ideal for compact rack installations and is suitable for use in schools, shops, restaurants, houses of worship and other presentation or entertainment venues.



Mixer Amplifier:

- 1U 19" Rack mountable chassis
- 120W Class-D amplifier
- Speaker outputs: 100V, 70V or 4 Ohm
- 4 Mic/Line inputs with Mic/Phantom/Line switch
- Aux line input, L/R RCA on rear panel (summed to mono)
- Mic.1 priority mute potentiometer
- Mute trigger via switched contact or alarm signal
- Channel level controls
- Echo effect with level control
- 2 Band EQ for bass and treble adjustments
- Master output level control
- 4 LED status indicators (signal, clip, protect, power)

Media Player:

- MP3 playback
- USB & Micro-SD (TF) ports
- FM tuner
- BT connectivity
- 3.5mm Aux jack input on front panel



General Specification:

- Mic/Line inputs: XLR/TRS 6.35mm Jack combo connectors
- Aux inputs: L/R RCA, 3.5mm Jack
- Speaker connection: screw terminals
- FM antenna connection: Coaxial
- Priority trigger connection: plug-in terminal block
- Operating supply voltage: 100-240V AC or 24V DC
- Dimensions (WxHxD): 483x44x281mm
- Weight: 4.9kg

The specifications above are correct at the time of printing this data sheet. For improvement purposes, all specifications for these units, including design and appearance, are subject to change without prior notice.