SIEMENS

Data sheet

3RW30 27-2BB04



SIRIUS SOFT STARTER, SIZE S0, 32A, 15KW/400V, 40 DEGREES, 200-480V AC, 24V AC/DC, SPRING-LOADED TERMINALS

General technical data:	
product brand name	SIRIUS
Product feature	
 integrated bypass contact system 	Yes
Thyristors	Yes
Product function	
 Intrinsic device protection 	No
 motor overload protection 	No
 Evaluation of thermistor motor protection 	No
External reset	No
 Adjustable current limitation 	No
• inside-delta circuit	No
Product component Motor brake output	 No
Equipment marking acc. to DIN EN 61346-2	 Q
Equipment marking acc. to DIN 40719 extended according to IEC 204-2 acc. to IEC 750	G

Power Electronics:			
	soft starters for standard applications		
А	32		
А	29		
А	26		
	A		

		7 500
— at standard circuit at 40 °C Rated value	W	7 500
• at 400 V		
— at standard circuit at 40 °C Rated value	W	15 000
yielded mechanical performance [hp] for three-phase	metric	7.5
AC motor at 200/208 V at standard circuit at 50 °C	hp	
Rated value		
Operating frequency Rated value	Hz	50 60
Relative negative tolerance of the operating	%	-10
frequency		
Relative positive tolerance of the operating frequency	%	10
Operating voltage at standard circuit Rated value	V	200 480
Relative negative tolerance of the operating voltage	%	-15
at standard circuit		
Relative positive tolerance of the operating voltage at	%	10
standard circuit		
Minimum load in % of I_M	%	10
Continuous operating current in % of I_e at 40 °C	%	115
Active power loss at operating current at 40 °C during	W	13
operation typical		
Control electronics:		
Type of voltage of the control supply voltage		AC/DC
Control supply voltage frequency 1 Rated value	Hz	50
Control supply voltage frequency 2 Rated value	Hz	60
Relative negative tolerance of the control supply	%	-10
Relative negative tolerance of the control supply voltage frequency	%	-10
	%	-10 10
voltage frequency		
voltage frequency Relative positive tolerance of the control supply		
voltage frequency Relative positive tolerance of the control supply voltage frequency		
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC	%	10
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value	% V	10 24
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value	% V V	10 24 24
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply	% V V	10 24 24
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz	% V V %	10 24 24 -15
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply	% V V %	10 24 24 -15
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz	% V V %	10 24 24 -15 10
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value	% V % %	10 24 24 -15 10 24
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply	% V % %	10 24 24 -15 10 24
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply voltage for DC	% V % % V	10 24 24 -15 10 24 -15
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply	% V % % V	10 24 24 -15 10 24 -15 10 24 -15
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Relative positive tolerance of the control supply	% V % % V	10 24 24 -15 10 24 -15 10 10 10 10 10 10 10 10
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal	% V % % V	10 24 24 -15 10 24 -15 10 10 10 10 10 10 10 10
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC at 50 Hz Rated value at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal	% V % % V	10 24 24 -15 10 24 -15 10 red
voltage frequency Relative positive tolerance of the control supply voltage frequency Control supply voltage 1 with AC • at 50 Hz Rated value • at 60 Hz Rated value Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Rated value Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal Mechanical data: Size of engine control device	% V % % V %	10 24 24 -15 10 24 -15 10 10 red

Depth	mm	150
Mounting type		screw and snap-on mounting
mounting position		With vertical mounting surface +/-10° rotatable, with vertical mounting surface +/- 10° tiltable to the front and back
Required spacing with side-by-side mounting		
• upwards	mm	60
• at the side	mm	15
 downwards 	mm	40
Installation altitude at height above sea level	m	5 000
Cable length maximum	m	300
Number of poles for main current circuit		3

Connections/ Terminals:

Type of electrical connection		
 for main current circuit 		spring-loaded terminals
 for auxiliary and control current circuit 		spring-loaded terminals
Number of NC contacts for auxiliary contacts		0
Number of NO contacts for auxiliary contacts		1
Number of CO contacts for auxiliary contacts		0
Type of connectable conductor cross-section for		
main contacts for box terminal using the front		
clamping point		
• solid		2x (1 2.5 mm²), 2x (2.5 6 mm²)
 finely stranded with core end processing 		2x (1 2.5 mm²), 2x (2.5 6 mm²)
Type of connectable conductor cross-section for		
AWG conductors for main contacts for box terminal		
 using the front clamping point 		1x 8, 2x (16 10)
Type of connectable conductor cross-section for		
main contacts		
• solid		1 10 mm²
 finely stranded with core end processing 		1 6 mm²
Type of connectable conductor cross-section for auxiliary contacts		
• solid		2x (0.25 2.5 mm²)
 finely stranded with core end processing 		2x (0.25 1.5 mm²)
Type of connectable conductor cross-section for AWG conductors	-	
• for main contacts		16 8
 for auxiliary contacts 		2x (24 14)
Ambient conditions:		
Ambient temperature		
 during operation 	°C	-25 +60
 during storage 	°C	-40 +80

Derating temperat	ture	°(C 40		
Protection class IF	D		IP2	0	
Certificates/ appro	ovals:				
General Produ	uct Approval			EMC	Test
					Certificates
					Type Test
(🔐)	(SP	(ŲL)	гні		Certificates/Test
ccc	CSA		LIIL	с-тіск	Report
	CJA	0L		CHER	
other					
other	Environmental	Declaration of			
	Confirmations	Conformity			

UL/CSA ratings:		
yielded mechanical performance [hp] for three-phase		
AC motor		
● at 220/230 V		
— at standard circuit at 50 °C Rated value	metric hp	7.5
● at 460/480 V		
— at standard circuit at 50 °C Rated value	metric hp	20
Contact rating of the auxiliary contacts acc. to UL		B300 / R300

urther informatior

Information- and Downloadcenter (Catalogs, Brochures,...) http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system) http://www.siemens.com/industrymall

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RW30272BB04

Service&Support (Manuals, Certificates, Characteristics, FAQs,...) http://support.automation.siemens.com/WW/view/en/3RW30272BB04/all

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/index.aspx?attID9=3RW30272BB04&lang=en







