Fair-Rite Products Corp.

Your Signal Solution®

## Toroids (5943004901)



Part Number: 5943004901

43 TOROID

Explanation of Part Numbers: - Digits 1 & 2 = Product Class - Digits 3 & 4 = Material Grade □- 9th digit 1 = Parylene Coating, 2 = Thermo- Set Plastic Coating

A ring configuration provides the ultimate utilization of the intrinsic ferrite material properties. Toroidal cores are used in a wide variety of applications such as power input filters, ground- fault interrupters, common- mode filters and in pulse and broadband transformers.

□All toroidal cores are supplied burnished to break sharp edges.

Coating Options:

 $\Box \Box$  – Toroids with an outside diameter of 9.5 mm (0.375") or smaller can be supplied Parylene C coated. The Parylene coating will increase the "A" and "C" dimensions and decrease the "B" dimension a maximum of 0.038 mm (0.0015"). The ninth digit of a Parylene coated toroid part number is a "1". See reference tables for the material characteristics of Parylene C. Parylene C coating is RoHS compliant.

 $\Box$  – Toroids with an outside diameter of 9.5 mm (0.375") or larger can be supplied with a uniform coating of thermo- set plastic coating. This coating will increase the "A" and "C" dimensions and decrease the "B" dimension a maximum of 0.5 mm (0.020"). The 9th digit of the thermo- set plastic coated toroid part number is a "2". Thermo- set plastic coating is RoHS compliant.  $\Box$  – Thermo- set plastic coated parts can withstand a minimum breakdown voltage of 1000 Vrms, uniformly applied across the "C" dimension of the toroid.

## □ For any toroidal core requirement not listed in the catalog, please contact our customer service department for availability and pricing.

The  $\Box C \Box$  dimension may be modified to suit specific applications.

Weight: 4 (g)

Dim	mm	mm tol	nominal inch	inch misc.	1.1
А	16	±0.40	0.63	_	
В	9.6	±0.30	0.378		$\left( \left( \right) \right)$
С	6.35	±0.25	0.25		
			<b>7</b>		




Chart Legend

 $\Sigma l/A$ : Core Constant,  $l_e$ : Effective Path Length, Effective Core Volume

A<sub>e</sub> : Effective Cross- Sectional Area,

V. :

Effective Core Volume  $A_t$ : Inductance Factor

Electrical Properties						
A <sub>L</sub> (nH)	520 ±20%					
$Ae(cm^2)$	0.199					
$\Sigma l / A(cm^{-1})$	19.4					
l <sub>e</sub> (cm)	3.85					
$V_{e}(cm^{3})$	0.77					

Toroids are tested for A<sub>1</sub> values at 10 kHz.

	Fair	- Rite Products Co	rp.	One Commercia	ıl Rov	v, Wallkill, New York 125	89-028	38
888-324-7748		845-895-2055		Fax: 845-895-2629		ferrites@fair- rite.com		www.fair- rite.com