

Advantages

Minimum size at high power

Low weight

Dual input and dual output voltage for series or parallel connection

Minimal no-load losses

Outstanding temperature behaviour thanks to low magnetic leakage field

Very low noise field


Applications

As a mains transformer for adjustment of the voltage and simple electrical isolation

As an isolating transformer for the safe electrical isolation of the input and output sides. The transformer may be used to set up protective separation as a protective measure in accordance with VDE 0100.

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Parallel connection (115V): brown with white/violet with blue Series connection (230V): violet with white

SEC:

Parallel connection: red with gresy/black with orange Series connection: black with grey

Standards

Isolating transformer to: VDE 0570 Teil 2-4, DIN EN 61558-2-4, EN 61558-2-4, IEC 61558-2-4, UL 5085-1/-2, CSA 22.2 No.66

Approvals



UL 5085-1/-2, CSA 22.2 No.66



Picture shows RKD 60 2x12



Mains transformer **RKD 30/2x24**

	Туре	RKD 30/2x24
30	Terminal and mounting	
	Fixing method	Mounting kit, M4 bolt
chanical data	Terminals	Connecting leads, 200 mm
	Measures and weights	
	Major diameter Ø	68 mm
	Outside diameter in the area of the wire lead \emptyset	71 mm
	Height without mounting	31 mm
	Weight	0.46 kg
ᄀ		

