

100V

OMNITRONIC ELA Transformer

100 V audio transformer

- 100 V Audio Transformer
- For amplifiers or speakers without built-in 100 V audio transformer
- Converts low-impedance signals into 100 V signals



No. 80711401	T5 5 W
No. 80711402	T10 10 W
No. 80711403	T20 20 W
No. 80711404	T30 30 W
No. 80711405	T50 50 W
No. 80711406	T75 75 W
No. 80711407	T100 100 W

Technical specifications:

Device:	ELA-T5	ELA-T10	ELA-T20	ELA-T30	ELA-T50	ELA-T75	ELA-T100
Frequency range:	50-15000 kHz	50-15000 kHz	40-17000 kHz	40-17000 kHz	30-15000 kHz	30-15000 kHz	30-15000 kHz
Power:	5 W RMS	10 W RMS	20 W RMS	30 W RMS	50 W RMS	75 W RMS	100 W RMS
Primary:	4/8/16 ohms	4/8/16 ohms	4/8/16 ohms	4/8/16 ohms	4/8/16 ohms	4/8/16 ohms	4/8/16 ohms
Secondary:	5/3.75/2.5/1.25/0.625 W	10/7.5/5/2.5/1.25 W	20/15/10/5/2.5 W	30/22.5/15/7.5/3.75 W	50/37.5/25/12.5/6.25 W	75/56.25/37.5/18.75/9.375 W	100/75/50/25/12.5 W
Dimensions:	60 x 35 x 35 mm	76 x 43 x 41 mm	71 x 44 x 44 mm	85 x 54 x 50 mm	93 x 57 x 56 mm	93 x 60 x 60 mm	93 x 66 x 60 mm
Weight:	180 g	300 g	400 g	675 g	900 g	950 g	1030 g

100V

OMNITRONIC ELA-100V-2-L Transformer

100 V transformer to units with line input

- 100 V input with screw plug terminal
- RCA and XLR output, unbalanced



No. 80711500

Technical specifications:

Input:	50 - 100 V
Outputs:	RCA, XLR
Dimensions:	157 x 90 x 60 mm
Weight:	500 g