Product data sheet Characteristics

GV4PEM03N

TeSys GV4 - thermal magnetic multifunction circuit breaker - 3.5A 3P - Everlink





Main

IVIAIII		
Range	TeSys	
Product name	TeSys GV4	
Device short name	GV4P	
Product or component type	Multifunction circuit breaker	
Device application	Motor	
Poles description	3P	
Utilisation category	Category A	
Trip unit technology	Thermal-magnetic Electronic	
Protection type	Ground fault protection Locked rotor Long start Short time short-circuit protection Phase unbalance Overload Short-circuit Jam Phase loss	
Motor tripping class	10 20	
[In] rated current	3.5 A	
Breaking capacity	65 kA at 208Y/120 V AC 50/60 Hz according to UL 60947 65 kA at 240 V AC 50/60 Hz according to UL 60947 35 kA at 480Y/277 V AC 50/60 Hz according to UL 60947 [[cu]: 100 kA at 220240 V AC 50/60 Hz according to IEC 60947-2 [[cu]: 50 kA at 380415 V AC 50/60 Hz according to IEC 60947-2 [[cu]: 50 kA at 440 V AC 50/60 Hz according to IEC 60947-2 [[cu]: 15 kA at 525 V AC 50/60 Hz according to IEC 60947-2 [[cu]: 8 kA at 660690 V AC 50/60 Hz according to IEC 60947-2 [[cu]: 25 kA at 500 V AC 50/60 Hz according to IEC 60947-2 [8 kA at 600Y/347 V AC 50/60 Hz according to UL 60947	
[lcs] rated service breaking capacity	100 kA : at 220240 V AC 50/60 Hz according to IEC 60947-2 50 kA : at 380415 V AC 50/60 Hz according to IEC 60947-2 50 kA : at 440 V AC 50/60 Hz according to IEC 60947-2	

25 kA : at 500 V AC 50/60 Hz according to IEC 60947-2 15 kA : at 525 V AC 50/60 Hz according to IEC 60947-2 2 kA : at 660...690 V AC 50/60 Hz according to IEC 60947-2

Trip unit rating	1.43.5 A
Control type	Toggle

Complementary

NFC
690 V AC 50/60 Hz conforming to IEC 60947-2
0.55 kW at 400415 V AC 50/60 Hz 0.75 kW at 400415 V AC 50/60 Hz 0.75 kW at 500 V AC 50/60 Hz 1.1 kW at 400415 V AC 50/60 Hz 1.1 kW at 500 V AC 50/60 Hz 1.1 kW at 500 V AC 50/60 Hz 1.1 kW at 660690 V AC 50/60 Hz 1.5 kW at 400415 V AC 50/60 Hz 1.5 kW at 500 V AC 50/60 Hz 1.5 kW at 500 V AC 50/60 Hz 1.5 kW at 660690 V AC 50/60 Hz 2.2 kW at 660690 V AC 50/60 Hz
8 kV according to IEC 60947-2
800 V conforming to IEC 60947-2
By clips By screws
Plate 75 mm symmetrical DIN rail 35 mm symmetrical DIN rail
Yes according to IEC 60947-1
40000 cycles
40000 cycles for AC-3 at 440 V In/2 40000 cycles for AC-3 at 440 V In
Green flag for presence of auxiliary contacts
1 slot(s) for alarm switch fault signalling contact (plug-in) 1 slot(s) for voltage release electrical remote tripping (plug-in) 1 slot(s) for auxiliary switch open/close contact (plug-in)
27 mm
EverLink BTR screw connectors - location: top socket 1 cable(s) 1.570 mm² (solid) EverLink BTR screw connectors - location: top socket 1 cable(s) 1.550 mm² (flexible) EverLink BTR screw connectors - location: bottom socket 1 cable(s) 2.595 mm² (solid) EverLink BTR screw connectors - location: bottom socket 1 cable(s) 2.570 mm² (flexible)
9 N.m for 1695 mm ² 5 N.m for 1.510 mm ²
20 mm
CE
CSA C22.2 No 60947-4-1 EN/IEC 60947-4-1 UL 60947-4-1 EN/IEC 60947-2
155 mm
81 mm
116 mm
1.45 kg
Grey (RAL 7016)

Environment

ZIII OIIII OIII	
Product certifications	IEC
Tropicalisation	2 according to IEC 68-2
IP degree of protection	IP40 (front face) according to IEC 60529
IK degree of protection	IK07 according to IEC 62262
Pollution degree	3 according to IEC 60947-1
Mechanical robustness	Shocks 15 Gn for 11 ms according to IEC 60068-2-27

Vibrations +/- 1 mm for 213.2 Hz according to IEC 60068-2-6	
Vibrations 0.7 gn for 13.2100 Hz according to IEC 60068-2-6	

Ambient air temperature for operation	-2570 °C
Ambient air temperature for storage	-5085 °C
Operating altitude	> 20005000 m with derating 2000 m without derating

Offer Sustainability

Sustainable offer status	Green Premium product	
RoHS (date code: YYWW)	Compliant - since 1736 - Schneider Electric declaration of conformity	
	Schneider Electric declaration of conformity	
REACh	Reference not containing SVHC above the threshold	
	Reference not containing SVHC above the threshold	
Product environmental profile	Available	
	Product environmental	
Product end of life instructions	Available	
	End of life manual	