SIEMENS

Data sheet 3RW30 16-2BB14



SIRIUS SOFT STARTER, SIZE S00, 9A, 4KW/400V, 40 DEGREES, 200-480V AC, 110-230V AC/DC, SPRING-LOADED TERMINALS

General technical data:		
product brand name		SIRIUS
Product feature		
 integrated bypass contact system 		Yes
Thyristors		Yes
Product function		
 Intrinsic device protection 		No
 motor overload protection 		No
 Evaluation of thermistor motor protection 		No
External reset		No
 Adjustable current limitation 		No
• inside-delta circuit		No
Product component Motor brake output		No
Equipment marking acc. to DIN EN 61346-2		Q
Equipment marking acc. to DIN 40719 extended according to IEC 204-2 acc. to IEC 750		G

Power Electronics:		
Product designation		soft starters for standard applications
Operating current		
• at 40 °C Rated value	Α	9
• at 50 °C Rated value	Α	8
• at 60 °C Rated value	Α	7
Mechanical power output for three-phase motors		
● at 230 V		

 — at standard circuit at 40 °C Rated value 	W	2 200
● at 400 V		
— at standard circuit at 40 °C Rated value	W	4 000
yielded mechanical performance [hp] for three-phase	metric	2
AC motor at 200/208 V at standard circuit at 50 °C	hp	
Rated value		
Operating frequency Rated value	Hz	50 60
Relative negative tolerance of the operating	%	-10
frequency		
Relative positive tolerance of the operating frequency	%	10
Operating voltage at standard circuit Rated value	V	200 480
Relative negative tolerance of the operating voltage	%	-15
at standard circuit		
Relative positive tolerance of the operating voltage at	%	10
standard circuit		
Minimum load in % of I_M	%	10
Continuous operating current in % of I_e at 40 °C	%	115
Active power loss at operating current at 40 °C during	W	1
operation typical		
Control electronics:		
Type of voltage of the control supply voltage		AC/DC
Control supply voltage frequency 1 Rated value	Hz	50
Control supply voltage frequency 2 Rated value	Hz	60
Relative negative tolerance of the control supply	%	-10
voltage frequency		
Relative positive tolerance of the control supply	%	10
voltage frequency		
Control supply voltage 1 with AC at 50 Hz	V	110 230
Control supply voltage 1 with AC at 60 Hz	V	110 230 110 230
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply		
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz	V %	110 230 -20
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply	V	110 230
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz	V %	110 230 -20 20
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC	V % %	110 230 -20 20 110 230
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz	V %	110 230 -20 20
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply	V % %	110 230 -20 20 110 230
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC	V % V %	110 230 -20 20 110 230 -20
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal	V % V %	110 230 -20 20 110 230 -20
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal	V % V %	110 230 -20 20 110 230 -20 20 red
Control supply voltage 1 with AC at 60 Hz Relative negative tolerance of the control supply voltage with AC at 60 Hz Relative positive tolerance of the control supply voltage with AC at 60 Hz Control supply voltage 1 for DC Relative negative tolerance of the control supply voltage for DC Relative positive tolerance of the control supply voltage for DC Display version for fault signal	V % V %	110 230 -20 20 110 230 -20

Medianical data.		
Size of engine control device		S00
Width	mm	45
Height	mm	120
Depth	mm	150

	screw and snap-on mounting
	With vertical mounting surface +/-10° rotatable, with vertical mounting surface +/- 10° tiltable to the front and back
mm	60
mm	15
mm	40
m	5 000
m	300
	3
	mm mm m

Connections/ Terminals:	
Type of electrical connection	
for main current circuit	spring-loaded terminals
 for auxiliary and control current circuit 	spring-loaded terminals
Number of NC contacts for auxiliary contacts	0
Number of NO contacts for auxiliary contacts	1
Number of CO contacts for auxiliary contacts	0
Type of connectable conductor cross-section for main contacts for box terminal using the front clamping point	
• solid	2x (1 2.5 mm²), 2x (2.5 6 mm²)
 finely stranded with core end processing 	2x (1.5 2.5 mm²), 2x (2.5 6 mm²)
Type of connectable conductor cross-section for AWG conductors for main contacts for box terminal	
using the front clamping point	2x (16 10)
Type of connectable conductor cross-section for main contacts	
• solid	1 4 mm²
 finely stranded with core end processing 	1 2.5 mm²
Type of connectable conductor cross-section for auxiliary contacts	
• solid	2x (0.25 2.5 mm²)
 finely stranded with core end processing 	2x (0.25 1.5 mm²)
Type of connectable conductor cross-section for AWG conductors	
• for main contacts	16 12
• for auxiliary contacts	2x (24 14)

Ambient conditions:		
Ambient temperature		
during operation	°C	-25 + 60
during storage	°C	-40 + 80
Derating temperature	°C	40

Protection class IP IP20

Certificates/ approvals:

General Product Approval

EMC

Test

Certificates











Type Test
Certificates/Test
Report

other

other

Declaration of Conformity

Environmental Confirmations

UL/CSA ratings:		
yielded mechanical performance [hp] for three-phase		
AC motor		
● at 220/230 V		
— at standard circuit at 50 °C Rated value	metric hp	2
● at 460/480 V		
— at standard circuit at 50 °C Rated value	metric hp	5
Contact rating of the auxiliary contacts acc. to UL		B300 / R300

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system)

http://www.siemens.com/industrymall

Cax online generator

 $\underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RW30162BB14}$

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

http://support.automation.siemens.com/WW/view/en/3RW30162BB14/all

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/index.aspx?attID9=3RW30162BB14&lang=en







