

Fusedrawer for Fuse Links 5x20mm resp. 6.3x32mm

Standard or Medical Fuse drawer



Fuse drawer "Fingerrip" with voltage selector
(Fuse links not enclosed)

Fuse drawer "Extrasafe" without voltage selector
(Fuse links not enclosed)



Description

- Component:
Snap-in, Rear Mounting
- 2 Functions:
Fuseholder for Fuse-links 5 x 20 mm or 6.3 x 32 mm, Voltage selector insert
- Approved together with power entry module

Characteristics

- Fuse drawer meets requirements of medical standard IEC/EN 60601-1
The fuse drawer "Fingerrip" can be removed by hand
For added safety "Extra-Safe" fuse drawers are available
With spare fuse compartment
- Suitable for use in equipment according to IEC 60950

Other versions on request

- Fuse drawer with other voltage values

References

Fits to type:

Weblinks

[pdf-datasheet](#), [html-datasheet](#), [General Product Information](#), [Approvals](#), [CE declaration of conformity](#), [RoHS](#), [CHINA-RoHS](#), [Mating Connectors](#), [e-Shop](#), [SCHURTER-Stock-Check](#), [Distributor-Stock-Check](#), [CAD-Drawings](#), [Accessories](#), [Mounting instruction](#), [Detailed request for product](#)

Voltage Selector Inserts

| Index | Marking on Voltage Selector Insert / Terminal No. | | | | | |
|-------|---|-------|-----|-------|-----|--|
| | KEC | 1 | 2 | 3 | 4 | |
| yy | KD | 3 | 4 | 5 | 6 | |
| 00 | | - | - | - | - | |
| 01 | | 100 | 120 | 220 | 240 | |
| 02 | | 110 | 150 | 220 | - | |
| 03 | | 110 | - | 220 | - | |
| 04 | | 110 | 220 | 240 | - | |
| 05 | | 115 | - | 230 | - | |
| 06 | | 117 | 220 | 240 | - | |
| 08 | | 110 V | - | 220 V | - | |
| 09 | | 220 | - | 240 | - | |
| 10 | | 115 | 220 | 240 | - | |
| 11 | | 110 | 120 | 220 | 240 | |
| 12 | | 115 | 230 | 240 | - | |
| 13 | | 100 | 110 | 220 | 240 | |
| 14 | | 100 | 117 | 220 | 240 | |
| 15 | | 100 | 115 | 230 | - | |
| 16 | | 100 | 120 | 230 | 240 | |
| 17 | | 115 | 120 | 230 | 240 | |
| 18 | | 115 | - | 240 | - | |
| 19 | | 220 | 120 | 240 | 230 | |
| 20 | | 100 | 120 | 230 | - | |
| 21 | | 100 | - | 220 | - | |
| 22 | | 100 | 120 | 220 | 230 | |
| 23 | | 100 | 110 | 120 | - | |
| 24 | | 200 | 220 | 240 | - | |

| Index yy | KEC KD | Marking on Voltage Selector Insert / Terminal No. | | | |
|-------------|-----------|---|--------|--------|--------|
| | | 1 3 | 2 4 | 3 5 | 4 6 |
| 25 | | 120 | - | 230 | - |
| 27 | | 115 | 200 | 230 | - |
| 28 | | - | 230 | 240 | - |
| 29 | | 100 | 117 | 125 | - |
| 30 | | 117 | 220 | 240 | 100 |
| 31 | | 117 | 220 | 240 | 100 |
| 32 | | 100 | 110 | 230 | 240 |
| 34 | | 110 | 115 | 230 | 240 |
| 35 | | 100 | 115 | 230 | 240 |
| 36 | | 100 | 110 | 200 | 230 |
| 37 | | 115 | 230 | 240 | 100 |
| 38 | | 110 | 230 | 220 | 240 |
| 39 | | 220 | 230 | 240 | - |
| 40 | | 100 | 110 | 127 | 230 |
| 42 | | 100 | 115 | 120 | 230 |
| 43 | | 115 | - | 230 | - |
| 44 | | 100 | 115 | 127 | 230 |
| 45 | | 100 | 115 | 230 | 127 |
| 46 | | 100 | 120 | 200 | 230 |
| 48 | | 100 | 120 | 208 | 230 |

Index "yy" matches the last two characters of the Order Number within the Variants

Variants

| Mounting | Fuse-Link | Fuseholder | Comment | Order Number |
|------------|-----------|------------|----------------------------------|--------------|
| Fingergrip | 5 x 20 | 1-pole | - | 4303.2114.yy |
| Extra-Safe | 5 x 20 | 1-pole | - | 4303.2124.yy |
| Fingergrip | 5 x 20 | 1-pole | - | 4303.2406 |
| Extra-Safe | 5 x 20 | 1-pole | - | 4303.2408 |
| Fingergrip | 5 x 20 | 1-pole | spare fuse case | 4303.2416 |
| Fingergrip | 5 x 20 | 2-pole | - | 4303.2014.yy |
| Extra-Safe | 5 x 20 | 2-pole | - | 4303.2024.yy |
| Fingergrip | 5 x 20 | 2-pole | - | 4303.2401 |
| Extra-Safe | 5 x 20 | 2-pole | - | 4303.2403 |
| Fingergrip | 5 x 20 | 2-pole | shorting bar on the neutral side | 4303.2036.yy |
| Extra-Safe | 5 x 20 | 2-pole | shorting bar on the neutral side | 4303.2037.yy |
| Fingergrip | 5 x 20 | 2-pole | shorting bar on the neutral side | 4303.2411 |
| Extra-Safe | 5 x 20 | 2-pole | shorting bar on the neutral side | 4303.2413 |
| Fingergrip | 6.3 x 32 | 1-pole | - | 4303.2614.yy |
| Extra-Safe | 6.3 x 32 | 1-pole | - | 4303.2624.yy |
| Fingergrip | 6.3 x 32 | 1-pole | - | 4303.2906 |
| Extra-Safe | 6.3 x 32 | 1-pole | - | 4303.2908 |
| Fingergrip | 6.3 x 32 | 2-pole | - | 4303.2514.yy |
| Extra-Safe | 6.3 x 32 | 2-pole | - | 4303.2524.yy |
| Fingergrip | 6.3 x 32 | 2-pole | - | 4303.2714.yy |
| Extra-Safe | 6.3 x 32 | 2-pole | - | 4303.2737.yy |
| Fingergrip | 6.3 x 32 | 2-pole | - | 4303.2901 |
| Extra-Safe | 6.3 x 32 | 2-pole | - | 4303.2903 |
| Fingergrip | 6.3 x 32 | 2-pole | shorting bar on the neutral side | 4303.2536.yy |
| Extra-Safe | 6.3 x 32 | 2-pole | shorting bar on the neutral side | 4303.2537.yy |
| Fingergrip | 6.3 x 32 | 2-pole | shorting bar on the neutral side | 4303.2911 |
| Extra-Safe | 6.3 x 32 | 2-pole | shorting bar on the neutral side | 4303.2913 |

"yy" see Voltage Selector Inserts Table

Packaging unit 50 Pcs
