## 2D/3D Profile Sensor

**MLWL125** Part Number

- Optimized profile quality thanks to HDR function
- Precise measuring range resolution X (> 2000 measuring points)
- Up to 12 million measuring points per second

2D/3D Profile Sensors project a laser line onto the object to be detected and generate an accurate, linearized height profile with an internal camera which is set up at a triangulation angle. Thanks to its uniform, open interface, the weCat3D series can be incorporated by means of the DLL program library or the GigE Vision standard without an additional control unit. Alternatively, wenglor offers its own software packages for implementing your application.

# LASER

#### **Technical Data**

Optical Data		
Working range Z	6001400 mm	
Measuring range Z	800 mm	
Measuring range X	450720 mm	
Linearity Deviation	200 <i>µ</i> m	
Resolution Z	2867 μm	
Resolution X	235361 μm	
Light Source	Laser (red)	
Wavelength	660 nm	
Laser Class (EN 60825-1)	2M	
Max. Ambient Light	5000 Lux	
Electrical Data		
Supply Voltage	1830 V DC	
Current Consumption (Ub = 24 V)	300 mA	
Measuring Rate	1756000 /s	
Subsampling	3506000 /s	
Temperature Range	045 °C	
Storage temperature	-2070 °C	
Inputs/Outputs	4	
Switching Output Voltage Drop	< 1,5 V	
Switching Output/Switching Current	100 mA	
Short Circuit Protection	yes	
Reverse Polarity Protection	yes	
Overload Protection	yes	
Interface	Ethernet TCP/IP	
Baud Rate	100/1000 Mbit/s	
Protection Class	III	
FDA Accession Number 1710274-000		
Mechanical Data		
Housing Material	Aluminum	
Degree of Protection	IP67	
Connection	M12 × 1; 12-pin	
Type of Connection Ethernet	M12 × 1; 8-pin, X-cod.	
Optic Cover	Glass	
Weight	2780 g	
Web server	yes	
Configurable as PNP/NPN/Push-Pull		
Switchable to NC/NO	Ŏ	
Connection Diagram No.	1022 1034	
Control Panel No.	X2 A22	
Suitable Connection Equipment No.	50 87	

Display brightness may decrease with age. This does not result in any impairment of the sensor function.



### **Complementary Products**

Cooling Unit ZLWK003 Protective Screen Retainer ZLWS003 Software Switch EHSS001

2D/3D Sensors

#### weCat3D





1 = Recommended mounting position based on the sensor's center of gravity All dimensions in mm (1 mm = 0.03937 Inch)



Legend					
+	Supply Voltage +				
-	Supply Voltage 0 V				
~	Supply Voltage (AC Voltage)				
А	Switching Output	(NO)			
Ā	Switching Output	(NC)			
V	Contamination/Error Output	(NO)			
V	Contamination/Error Output	(NC)			
E	Input (analog or digital)				
Т	Teach Input				
Z	Time Delay (activation)				
S	Shielding				
RxD	Interface Receive Path				
TxD	Interface Send Path				
RDY	Ready				
GND	Ground				
CL	Clock				
E/A	Output/Input programmable				
0	IO-Link				
PoE	Power over Ethernet				
IN	Safety Input				
OSSD	Safety Output				
Signal	Signal Output				
BI_D+/-	Ethernet Gigabit bidirect. data line (A-D)				
ENnes42	Encoder 0-pulse 0-0 (TTL)				

Ctrl. Panel	
A22	X2
8	60
<sup>78</sup> () 49 ()	
20 = Enter Button 22 = UP Button 23 = Down Button	

4a = User LED

60 = Display

68 = Supply Voltage Indicator

78 = Module status

85 = Link/Act LED

PT	Platinum measuring resistor	ENARS422	Encoder A/Ā (TTL)
nc	not connected	ENBR5422	Encoder B/B (TTL)
U	Test Input	ENa	Encoder A
Ū	Test Input inverted	ENв	Encoder B
W	Trigger Input	Amin	Digital output MIN
W -	Ground for the Trigger Input	Амах	Digital output MAX
0	Analog Output	Аок	Digital output OK
0-	Ground for the Analog Output	SY In	Synchronization In
BZ	Block Discharge	SY OUT	Synchronization OUT
Awv	Valve Output	OLT	Brightness output
а	Valve Control Output +	м	Maintenance
b	Valve Control Output 0 V	rsv	reserved
SY	Synchronization	Wire Co	olors according to IEC 60757
SY-	Ground for the Synchronization	BK	Black
E+	Receiver-Line	BN	Brown
S+	Emitter-Line	RD	Red
÷	Grounding	OG	Orange
SnR	Switching Distance Reduction	YE	Yellow
Rx+/-	Ethernet Receive Path	GN	Green
Tx+/-	Ethernet Send Path	BU	Blue
Bus	Interfaces-Bus A(+)/B(-)	VT	Violet
La	Emitted Light disengageable	GY	Grey
Mag	Magnet activation	WH	White
RES	Input confirmation	PK	Pink
EDM	Contactor Monitoring	GNYE	Green/Yellow

Measuring field X, Z



