



SIMATIC S7-300, SIMULATOR MODULE SM 374, FOR SIMULATING 16 INPUTS OR 16 OUTPUTS RESP. 8 INPUTS AND 8 OUTPUTS; 16 SWITCHES, 16 LED

Input current	
from backplane bus 5 V DC, max.	80 mA
Power losses	
Power loss, typ.	0.35 W
Digital inputs	
Number of digital inputs	16; Switches
Digital outputs	
Number of digital outputs	16; LEDs
Analog inputs	
Number of analog inputs	0
Analog outputs	
Number of analog outputs	0
Galvanic isolation	
Galvanic isolation digital inputs	
• between the channels and the backplane bus	No
Galvanic isolation digital outputs	
• between the channels and the backplane bus	No
Dimensions	
Width	40 mm
Height	125 mm
Depth	120 mm
Weights	

Weight, approx.

190 g

last modified:

12.03.2015