

## Signalling switch ready to switch-on, 1W



Part no. IZMX-LCS-1 Article no. 184104 Catalog No. 67C2814G33

**Delivery programme** 

Product range	Accessories
Accessories	Auxiliary contact
Accessories	Operational readiness indicator
	1 changeover contact
For use with	IZMX16, IZMX40 INX16, INX40
Instructions	$\label{thm:constraints} For signaling availability. Alternatively, also for automatic closing upon availability.$
	OFF message

## **Technical data**

**Rated breaking capacity** 

Inductive load		
250 V AC	Α	10
125 V DC	Α	0.5
250 V DC	Α	0.25

## Design verification as per IEC/EN 61439

Technical data for design verification		
Operating ambient temperature min.	°C	-25
Operating ambient temperature max.	°C	70

## **Technical data ETIM 6.0**

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ec/@ss8 1-27-37-13-02 [AKN342010])

(ecl@ss8.1-27-37-13-02 [AKN342010])		
Number of contacts as change-over contact		1
Number of contacts as normally open contact		0
Number of contacts as normally closed contact		0
Rated operation current le at AC-15, 230 V	Α	10
Type of electric connection		Flat plug-in connection
Model		Half-integrated
Mounting method		