

JBC JNASE

High-Precision Hot Air



Product Application Map

News



JNASE is the only Hot Air Station to **rework SMDs without affecting nearby components.**

It is the perfect station for easy and high-precision reworking of components as small as 01005, even under the magnifying glass.

Includes:

- NH High-Precision Heater Hose Set which works with J125 Cartridge Range.



J125010 - Ø1
Included



J125410 - Ø1



J125030 - Ø3

- T260 Pick & Place to position and remove components easily thanks to the built-in suction pump.

Check out more information about features of Hot Air Stations.

**Don't believe us...
TRY IT!**



REFERENCES

- JNASE-9A 100 V
- JNASE-1A 120 V
- JNASE-2A 230 V

PRODUCT COMPOSITION

- 1 JNASE High-Precision Hot Air Control Unit

SPECIFICATIONS

Nominal power	70W
Selectable temperature	150 to 450 °C / 300 to 840 °F
Air flow regulation	0.15 - 2.5 SLPM
Vacuum	53% / 397 mmHg / 15.6 inHg
ESD safe	Meet ANSI / ESD S20.20-2021
Equipotential bonding	Connection to EPA

1 NH High-Precision Heater Hose Set	USB-A	Firmware update
1 NAS Stand for NH High-Precision Heater Hose Set		Graphics and profiles
1 J125010 Cartridge Ø 1	USB-B	PC communications
1 T260 Pick & Place	RJ12 Connector	Remote control or FAE Fume Extractor connection
1 NBC260 Bent Needles & cups for T260		
1 P405 Pedal	Pedal Connector	Tool control
<u>WEIGHT AND DIMENSIONS</u>		
	Control Unit	180 x 170 x 110 mm / 2.83 kg. 7.09 x 6.69 x 4.33 in / 6.23 lb.
	Package	425 x 295 x 495 mm / 4.20 kg. 16.73 x 11.61 x 19.49 in / 9.26 lb.

Copyright © 2023 JBC Soldering S.L. | [Legal Notice](#) | [Privacy Policy](#) | [Terms and Conditions](#) | [Cookie policy](#) | [RSS Feed](#) | [JBC Store](#) | [Contact Us](#)

CONNECTABLES

PreHeater



PHNEK

Preheater Set for PCBs up to 11 x 7 cm / 4 x 3"



PHSEK

Preheater Set for PCBs up to 13 x 13 cm / 5 x 5"



RHS-A

Articulated Hand Rest with base for PHSEK



HRL-A

Articulated Left Hand Rest