9.5 DEOS® ST 172 SAFETY starter

Technical information



Made in Its

DEOS St 172 SAFETY starter for fluorescent lamps in series circuits

Product features

- DEOS St 172 SAFETY starter for fluorescent lamps L15W ...22W and OSRAM DULUX[®] L 18W in series circuits for inductive (> 20,000 switching cycles) and capacitive operation (> 10,000 switching cycles).
- Reliably disconnects faulty lamps under inductive or capacitive operating conditions. There is therefore no need to replace a single faulty lamp instantly. This in turn means longer re-lamping intervals and greater efficiency.
- Prevents unnecessary power consumption due to short-circuit currents as DEOS St 172 SAFETY switch-off at the end of lamp life.
- Protects the control gear and luminaire holders.

Extension of lamp life by 20%.

- With red SAFETY button which can be reset for immediate operation again.
- Service life: DEOS St 172 SAFETY starter approx. 4 years inductive and approx. 2 years capacitative (for 2 switching operations per day).
- Reason: Both lamp electrodes are evenly heated each time the lamp is ignited thanks to the symmetrical design of the bimetallic strip.
- Self-extinguishing plastic casing made of Makrolon. Class V0
- Equipped with special radio-interference suppression capacitor (foil winding capacitor)
- Suitable for 220V-240V AC operation, 50/60 Hz series circuits and single circuits 18W ...22W at 110V/127V
- Cannot be used for OSRAM DULUX® S/E, D/E, T/E or T/E IN.
- When the luminaire is used for the first time, push in the red SAFETY button until it clicks.
- Application: For indoor and outdoor lighting, particularly where it is essential for burnt-out lamps to be reliably shut down.

Temperature range	-20°C to +80°C		
Approval marks	ENEC 10 VDE		
Label	CE label since 01.01.97		
Protection class	Protection class II		
Dimensions	According to international standard IEC 155, as per Fig. B.1 Length IEC max. 40.3 mm Diameter IEC max. 21.5 mm		
Range	Reference	Standard pack	EAN
	St 172 8x25er Tray OSRAM	25/200	4050300854069
Availability	From stock		

