Note: This datasheet may be out of date. Please download the latest datasheet of LQW18AN33NJ10# from the official website of Murata Manufacturing

LQW18AN33NJ10#

"#" indicates a package specification code.

Size Code 1608 (0603) in mm (in inch), High Q, Low DC Resistance Type




















< List of part numbers with package codes > LQW18AN33NJ10B LQW18AN33NJ10J LQW18AN33NJ10D



Appearance & Shape





(in mm)

References

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	500
J	330mm Paper Tape	10000
D	180mm Paper Tape	4000

Mass (typ.)	
1 piece	0.003g

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LQW18AN33NJ10#

Co., Ltd.

Note: This datasheet may be out of date

Please download the latest datasheet of LQW18AN33NJ10# from the official website of Murata Manufacturing

"#" indicates a package specification code.



L size	1.6±0.2mm
W size	0.8±0.3mm
T size	0.8±0.2mm
Size code inch (mm)	0603 (1608)
Inductance	33nH±5%
Inductance Test Frequency	100MHz
Rated current (Itemp) (Based on Temperature rise)	550mA
Max. of DC resistance	0.132Ω
Q(min.)	42
Q Test Frequency	250MHz
Self resonance frequency (min.)	2500MHz
Operating Temperature Range(Self- temperature rise is not included)	-55°C to 125°C
Series	LQW18AN_10

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LQW18AN33NJ10#

"#" indicates a package specification code.



The charts below may show another part number which shares its characteristics.





Frequency Characteristic (Z) 1200 Impedance[ohm]
800
800
400
200 200 10M 100M 10G Frequency[Hz]

LQW18AN33NJ10 |Z|

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

