

VOLTCRAFT®

VOLTCRAFT® - TOP PERFORMANCE IN EVERY WAY

"Since 1982, our product range has been dynamically adapting to the constant changes in the industry. We commit to offering first-class quality to our customers while delivering an excellent cost-performance ratio. This philosophy remains the cornerstone of Voltcraft's success."

VC-35 ROTARY FIELD TESTER

CE
VERSION 12/21

N° 1017868

Automatic testing device for displaying and testing the phase sequence and rotary field direction of the external line in industrial electrical installations.



FEATURES:

- Automatic test process //
- Phase sequence and rotational direction display //
- Large, easy-to-read LCD display.

EQUIPMENT:

- Plug-in measurement leads //
- Clip-on alligator clips.

PACKAGE CONTENTS:

- 3 safety measurement lines //
- 3 alligator clips //
- Bag //
- Operating instructions.

TECHNICAL DATA:

Measurement voltage:	40 - 700 V/AC
Frequency range:	15 - 400 Hz
Connection:	4 mm safety sockets
Display:	LCD
Measurement category:	CAT IV 600 V
Dimensions (L x W x H):	29 x 71 x 123 mm
Weight:	160 g

Legal notice

This data sheet is published by Conrad Electronic SE, Klaus-Conrad-Str. 1, D-92240 Hirschau (www.conrad.com). All rights including translation reserved. Reproduction by any method, e.g. photocopy, microfilming, or the capture in electronic data processing systems require the prior written approval by the editor. Reprinting, also in part, is prohibited. This data sheet represent the technical status at the time of printing.

© Copyright 2022 by Conrad Electronic SE

1017868_V4_1221_01_PIX_ds