#### PEL 230/12-6,5



## Advantages

Stabilised and adjustable output voltage

DC OK signalling via LEDs

Parallel connection option

Service-friendly spring-loaded connector system

Panel installation on mounting rails

## **Applications**

Primary switch mode power supply is concentrated on the core task of voltage and current supply. Flat step profile optimized for installation in control panels in the building automation.

### Standards

Primary switched mode power supply to UL 60950, UL 508

EN 61558-2-16, EN 60950-1

EMC: EN 61204-3 **Approvals** 







UL/CSA 60950 recognised, UL508 listed, Germanischer Lloyd





# Single phase, primary switched mode power supply **PEL 230/12-6,5**

Type	PEL 230/12-6,5
Input Input rated voltage	
Input rated voltage	100 - 240 Vac
Input voltage range	85 - 264 Vac (120 - 373 Vdc)
Input rated current (rated load)	1.5 / 0.5 A (110 / 230 Vac)
Rated frequency range	44 - 66 Hz / 0 Hz
Starting current limiter	<30 A, NTC
Input fuse internal	4 A
Recommended back-up fuse (circuit breaker)	6 A, 10 A, 16 A, characteristics B, C
Input rated current (rated load) Rated frequency range Starting current limiter Input fuse internal Recommended back-up fuse (circuit breaker) Mains buffering Transient surge voltage protection	15 / 100 ms
Transient surge voltage protection	Varistor
Output	
Output rated voltage	12 Vdc ±2 %
Output voltage range	10.5 - 15.5 Vdc
Output rated current	6.50 A
Resistance to reverse feed max.	25 Vdc
Overload behaviour	Constant current
Ripple factor	typ. 100 mVss
Parallel connection	Yes
Serial operation	Yes
Efficiency	typ. 87 %
Signaling	
Power Good (DC OK)	LED green
Standards	
Classification	Primary switched mode power supply
Approvals	
Approvals	cURus, cULus, GL
Environment	
Ambient temperature	-25° C to +55° C
Storage temperature	-25° C to +85° C
Derating	-3 %/K > +45° C
Current capacity by any mounting position	max. 3.9 A
Safety and protection	
Protection index	IP 20
Safety class	II, (in closed cabinet)
Order numbers	
Order Number	PEL 230/12-6,5



