

Multimeter

LCR



Specifications	Range	Best Accuracy
Resistance (Ω)	20 Ω / 200 Ω / 2 k Ω / 20 k Ω / 200 k Ω / 2 M Ω / 20 M Ω / 200 M Ω / 2,000 M Ω	
	20 Ω / 200 Ω / 2 k Ω / 20 k Ω / 200 k Ω / 2 M Ω / 20 M Ω / 200 M Ω / 2,000 M Ω	
	200 Ω / 2 k Ω / 20 k Ω / 200 k Ω / 2 M Ω / 20 M Ω	$\pm (0.8\% + 1)$
Capacitance (C)	200 pF / 2 nF / 20 nF / 200 nF / 2 μ F / 20 μ F / 200 μ F / 2 mF / 20 mF	
	2 nF / 20 nF / 200 nF / 2 μ F / 20 μ F / 200 μ F / 600 μ F	$\pm (1\% + 5)$
Inductance (H)	2 mH / 20 mH / 200 mH / 2 H / 20 H / 200 H	
	2 mH / 20 mH / 200 mH / 2H / 20 H	$\pm (2\% + 8)$
Features		
Display count	1,999	
Manual range	✓	
Diode	✓	
Transistor	✓	
Continuity buzzer	✓	
Low battery indication	✓	
Data hold	✓	



Multimeter

LCR



General Characteristics

Power	9 V battery (6F22)
LCD size	61 x 32 mm
Product colour	Red and grey
Product net weight	312 g
Product size	172 x 83 x 38 mm
Standard accessories	Battery, test clip, holster
Standard individual packing	Gift box, English manual
Standard quantity per carton	40 pieces
Standard carton measurement	598 x 418 x 340 mm (0.085 cbm per standard carton)
Standard carton gross weight	21 kg

Part Number Table

Description	Part Number
Multimeter, LCR	72-8155

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. TENMA™ is the registered trademark of the Group. © Premier Farnell plc 2011.

