



Signalling switch, circuit-breaker position, 1W, right or left

Part no. IZMX-CS40-1
Article no. 184196
Catalog No. 65A2788G31

Delivery programme

Product range			Accessories
Accessories			Withdrawable units
Accessories			Position signalling switches
			One changeover contact each for the Disconnected, Test, and Connected positions. for fitting to left or right
For use with			IZMX-CAS40...
Installation type			Withdrawable

Technical data

Rated breaking capacity

Inductive load			
250 V AC		A	10
125 V DC		A	0.5
250 V DC		A	0.25

Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecl@ss8.1-27-37-13-02 [AKN342010])			
Number of contacts as change-over contact			1
Number of contacts as normally open contact			2
Number of contacts as normally closed contact			2
Rated operation current I _e at AC-15, 230 V		A	10
Type of electric connection			Flat plug-in connection
Model			Half-integrated
Mounting method			Floor fastening