

Note: This datasheet may be out of date.

Please download the latest datasheet of BNX023-01# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX023-01%23

"#" indicates a package specification code.








< List of part numbers with package codes > BNX023-01B BNX023-01K BNX023-01L



### Appearance & Shape







## **Packaging Information**

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
K	330mm Embossed Tape	1500
L	180mm Embossed Tape	400



## **Applications**

Other Usage

For general

1 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Note: This datasheet may be out of date.

Please download the latest datasheet of BNX023-01# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX023-01%23

"#" indicates a package specification code.



BNX022/023/028/029 is SMD type high performance and provides excellent noise suppression on DC power lines.

#### Features

- 1. Large rated current (20A)
- 2. Supporting wide frequency range From 15kHz to 1GHz:35dB min.(BNX029)
- 3. Mounting area and volume is reduced.
- 4. Effective for impulse noise such as electrostatic discharge or spike noise.

#### **Applications**

- 1. Displays (PDP/LCD-TV)
- 2. Digital AV equipment
- 3. Amusement equipment
- 4. PC peripheral equipment
- 5. Industry equipment, measurement equipment, power supplies

2 of 4

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: This datasheet may be out of date.

Please download the latest datasheet of BNX023-01# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX023-01%23

"#" indicates a package specification code.



# Specifications

Shape	SMD	
Length	12.1mm	
Length Tolerance	±0.2mm	
Width	9.1mm	
Width Tolerance	±0.2mm	
Thickness	3.1mm	
Thickness Tolerance	±0.2mm	
Rated Current	20A	
Operating Temperature Range	-40°C to 125°C	
Mass(typ.)	0.8g	
Rated Voltage	100Vdc	
Withstanding Voltage	250Vdc	
Insulation Resistance(min.)	500ΜΩ	
Insertion Loss	1MHz to 1GHz:35dB min. (Line impedance=50Ω)	

3 of 4

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date.


Please download the latest datasheet of BNX023-01# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX023-01%23

"#" indicates a package specification code.








#### **Insertion Loss Characteristics**

In operating temperature exceeding +85°C, derating of current is necessary for BNX023/029 series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



**Equivalent Circuit** 

**Derating of Rated Current** 

4 of 4

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

