

M8 MALE FLANGE PLUG FRONT MOUNT


TPE wires 3x0.25 0.5m

Flange M8 male 3-pole Front mounting with multi-strand wire

Link to Product

Illustration







The information in this brochure has been compiled with the utmost care. Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/15

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.de | shop.murrelektronik.de

stay connected



Male



Product may differ from Image

Form		
	08552	
Technical Data		
Operating voltage	max. 60 V AC/DC	
Operating current per contact	max. 4 A	
Locking of ports	Screw thread M8 \times 1 mm (recommended torque 0.4 Nm) self-securing	
Protection	IP67 inserted and tightened (EN 60529)	
Cables		
Cable number	970	
No./diameter of wires	3 × 0.25 mm ²	
Wire isolation	PP (br, bk, bl)	
Shore hardness outer jacket	70 ± 5D	
Outer diameter	approx. 1.25 mm	
Bend radius (fixed)	5 × outer Ø	
Bend radius (moving)	10 × outer Ø	
Temperature range (fixed)	-40+80 °C	
Temperature range (mobile)	-25+80 °C	
General data		
Temperature range	-25+85 °C	

The information in this brochure has been compiled with the utmost care. Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/15

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.de | shop.murrelektronik.de



		stay connected
Commercial data		
country of origin	DE	
customs tariff number	85444290	
minimum order quantity	1	

The information in this brochure has been compiled with the utmost care. Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/15

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.de | shop.murrelektronik.de