

XF204-2BA IRT managed IE IRT Switch, 4 x 10/100MBit/s, 2 x bus adapter interface fault signal contact, with set button, redundant 24 V DC power supply, PROFINET IO Device, Network management, redundancy manager integrated, incl. electron. manual on CD-ROM, C-plug optional



### Transmission rate

Transfer rate	10 Mbit/s, 100 Mbit/s
---------------	-----------------------

### Interfaces / for communication / integrated

Number of electrical connections	0
<ul style="list-style-type: none"> <li>for network components or terminal equipment</li> </ul>	0

### Interfaces / others

Number of electrical connections	
<ul style="list-style-type: none"> <li>for signaling contact</li> </ul>	1
<ul style="list-style-type: none"> <li>for power supply</li> </ul>	1
<ul style="list-style-type: none"> <li>for redundant voltage supply</li> </ul>	1

Type of electrical connection	
<ul style="list-style-type: none"> <li>for signaling contact</li> </ul>	2-pole terminal block
<ul style="list-style-type: none"> <li>for power supply</li> </ul>	2-pole terminal block

design of the removable storage	
<ul style="list-style-type: none"> <li>C-PLUG</li> </ul>	Yes

### Signal-Inputs/outputs

Operating voltage / of the signaling contacts	
---	--

<ul style="list-style-type: none"> <li>• at DC / Rated value</li> </ul>	24 V
Operating current / of the signaling contacts	
<ul style="list-style-type: none"> <li>• at DC / maximum</li> </ul>	0.1 A

### Supply voltage, current consumption, power loss

Type of voltage / of the supply voltage	DC
Supply voltage	
<ul style="list-style-type: none"> <li>• external</li> </ul>	24 V
<ul style="list-style-type: none"> <li>• external / minimum</li> </ul>	19.2 V
<ul style="list-style-type: none"> <li>• external / maximum</li> </ul>	28.8 V
Product component / fusing at power supply input	Yes
Consumed current / maximum	0.4 A
Power loss [W]	
<ul style="list-style-type: none"> <li>• at DC / at 24 V</li> </ul>	7.2 W

### Permitted ambient conditions

Ambient temperature	
<ul style="list-style-type: none"> <li>• during operation</li> </ul>	-30 ... +60 °C
<ul style="list-style-type: none"> <li>• during storage</li> </ul>	-40 ... +85 °C
<ul style="list-style-type: none"> <li>• during transport</li> </ul>	-40 ... +85 °C
Relative humidity	
<ul style="list-style-type: none"> <li>• at 25 °C / without condensation / during operation / maximum</li> </ul>	95 %
Protection class IP	IP20

### Design, dimensions and weight

Width	100 mm
Height	117 mm
Depth	74 mm
Net weight	0.25 kg
Mounting type	
<ul style="list-style-type: none"> <li>• 35 mm DIN rail mounting</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• wall mounting</li> </ul>	No
<ul style="list-style-type: none"> <li>• S7-300 rail mounting</li> </ul>	No
<ul style="list-style-type: none"> <li>• S7-1500 rail mounting</li> </ul>	No

### Product properties, functions, components / general

Cascading in the case of a redundant ring / at reconfiguration time of <math>\sim 0.3\text{ s}</math>	50
Cascading in cases of star topology	any (depending only on signal propagation time)

### Product functions / management, configuration

Product function	
<ul style="list-style-type: none"> <li>• CLI</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• web-based management</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• MIB support</li> </ul>	Yes

• TRAPs via email	Yes
• Configuration with STEP 7	Yes
• Port mirroring	No
• multiport mirroring	No
• with IRT / PROFINET IO switch	Yes
• PROFINET IO diagnosis	Yes
• switch-managed	Yes
<hr/>	
Protocol / is supported	
• Telnet	Yes
• HTTP	Yes
• HTTPS	Yes
• TFTP	Yes
• FTP	Yes
• BOOTP	No
• DCP	Yes
• LLDP	Yes
• SNMP v1	Yes
• SNMP v2	Yes
• SNMP v3	Yes
<hr/>	
Identification & maintenance function	
• I&M0 - device-specific information	Yes
• I&M1 – higher-level designation/location designation	Yes

### Product functions / Diagnosis

Product function	
• Port diagnostics	Yes
• Statistics Packet Size	Yes
• Statistics packet type	Yes
• Error statistics	Yes

### Product functions / DHCP

Product function	
• DHCP client	Yes

### Product functions / Redundancy

Product function	
• Ring redundancy	Yes
• High Speed Redundancy Protocol (HRP)	Yes
• high speed redundancy protocol (HRP) with redundancy manager	Yes
• high speed redundancy protocol (HRP) with standby redundancy	Yes

Protocol / is supported / Media Redundancy Protocol (MRP)	Yes
Product function	
<ul style="list-style-type: none"> <li>• media redundancy protocol (MRP) with redundancy manager</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Media Redundancy Protocol for Planned Duplication (MRPD)</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Parallel Redundancy Protocol (PRP)/operation in the PRP-network</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Parallel Redundancy Protocol (PRP)/Redundant Network Access (RNA)</li> </ul>	No
<ul style="list-style-type: none"> <li>• Passive listening</li> </ul>	Yes

#### Product functions / Security

Protocol / is supported	
<ul style="list-style-type: none"> <li>• SSH</li> </ul>	Yes

#### Product functions / Time

Product function	
<ul style="list-style-type: none"> <li>• SICLOCK support</li> </ul>	Yes
Protocol / is supported	
<ul style="list-style-type: none"> <li>• NTP</li> </ul>	No
<ul style="list-style-type: none"> <li>• SNTP</li> </ul>	Yes

#### Standards, specifications, approvals

Standard	
<ul style="list-style-type: none"> <li>• for FM</li> </ul>	FM3611: Class 1, Divison 2, Group A, B, C, D / T4, CL.1, Zone 2, GP. IIC, T4
<ul style="list-style-type: none"> <li>• for hazardous zone</li> </ul>	EN 60079-0 : 2006, EN 60079-15: 2005, II 3 G Ex nA II T4 KEMA 07 ATEX 0145X
<ul style="list-style-type: none"> <li>• for safety / from CSA and UL</li> </ul>	UL 60950-1, CSA C22.2 No. 60950-1
<ul style="list-style-type: none"> <li>• for hazardous zone / from CSA and UL</li> </ul>	ANSI / ISA 12.12.01, CSA C22.2 No. 213-M1987, CL. 1 / Div. 2 / GP. A, B, C, D T4, CL. 1 / Zone 2 / GP. IIC, T4
<ul style="list-style-type: none"> <li>• for emitted interference</li> </ul>	EN 61000-6-4:2001 (Class A)

#### Standards, specifications, approvals / CE

Certificate of suitability / CE marking	Yes
---	-----

#### Standards, specifications, approvals / miscellaneous

Certificate of suitability	EN 61000-6-2, EN 61000-6-4
<ul style="list-style-type: none"> <li>• C-Tick</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Railway application in accordance with EN 50155</li> </ul>	No
<ul style="list-style-type: none"> <li>• Railway application in accordance with EN 50124-1</li> </ul>	No
<ul style="list-style-type: none"> <li>• KC approval</li> </ul>	Yes

## Standards, specifications, approvals / product conformity

MTBF / at 40 °C 78.83 y

## Accessories

Product extension / optional / C-PLUG Yes

## Further Information / Internet Links

### Internet-Link

- to website: Selector SIMATIC NET SELECTION TOOL <http://www.siemens.com/snst>
- to website: Industrial communication <http://www.siemens.com/simatic-net>
- to website: Industry Mall <https://mall.industry.siemens.com>
- to website: Information and Download Center <http://www.siemens.com/industry/infocenter>
- to website: Image database <http://automation.siemens.com/bilddb>
- to website: CAx Download Manager <http://www.siemens.com/cax>
- to website: Industry Online Support <https://support.industry.siemens.com>

## Security information

### Security information

Siemens provides products and solutions with industrial security functions that support the secure operation of plants, solutions, machines, equipment and/or networks. They are important components in a holistic industrial security concept. With this in mind, Siemens' products and solutions undergo continuous development. Siemens recommends strongly that you regularly check for product updates. For the secure operation of Siemens products and solutions, it is necessary to take suitable preventive action (e.g. cell protection concept) and integrate each component into a holistic, state-of-the-art industrial security concept. Third-party products that may be in use should also be considered. For more information about industrial security, visit <http://www.siemens.com/industrialsecurity>. To stay informed about product updates as they occur, sign up for a product-specific newsletter. For more information, visit <http://support.automation.siemens.com>. (V3.4)

**last modified:**

09/20/2017