



SIMATIC S7-1500 analog input module AI 8xU/R/RTD/TC HF, 16 bit resolution, up to 21 bit Resolution at RT and TC, accuracy 0.1%, 8 channels in groups of 1; common mode voltage: 30 V AC/60 V DC, Diagnostics; Hardware interrupts Scalable temperature measuring range, thermocouple type C, Calibrate in RUN; Delivery including infeed element, shield bracket and shield terminal: Front connector (screw terminals or push-in) to be ordered separately

General information	
Product type designation	AI 8xU/R/RTD/TC HF
HW functional status	FS01
Firmware version	V1.1.0
<ul style="list-style-type: none"> FW update possible 	Yes
Product function	
<ul style="list-style-type: none"> I&M data 	Yes; I&M0 to I&M3
<ul style="list-style-type: none"> Isochronous mode 	No
<ul style="list-style-type: none"> Prioritized startup 	Yes
<ul style="list-style-type: none"> Measuring range scalable 	Yes
<ul style="list-style-type: none"> Scalable measured values 	No
<ul style="list-style-type: none"> Adjustment of measuring range 	No
Engineering with	
<ul style="list-style-type: none"> STEP 7 TIA Portal configurable/integrated from version 	V14 / -
<ul style="list-style-type: none"> STEP 7 configurable/integrated from version 	V5.5 SP3 / -
<ul style="list-style-type: none"> PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
<ul style="list-style-type: none"> PROFINET from GSD version/GSD revision 	V2.3 / -
Operating mode	
<ul style="list-style-type: none"> Oversampling 	No
<ul style="list-style-type: none"> MSI 	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	55 mA; with 24 V DC supply
Power	
Power available from the backplane bus	0.85 W
Power loss	
Power loss, typ.	1.9 W
Analog inputs	
Number of analog inputs	8; Plus one additional RTD (reference) channel
<ul style="list-style-type: none"> For voltage measurement 	8; Plus one additional RTD (reference) channel
<ul style="list-style-type: none"> For resistance/resistance thermometer 	8; Plus one additional RTD (reference) channel

measurement	
• For thermocouple measurement	8; Plus one additional RTD (reference) channel
permissible input voltage for voltage input (destruction limit), max.	20 V
Constant measurement current for resistance-type transmitter, typ.	150 Ohm, 300 Ohm, 600 Ohm, Cu10, Cu50, Cu100, Ni10, Ni100, Ni120, Ni200, Pt10, Pt50, Pt100, Pt200 climate: 1 mA; 6 kOhm, Ni500, Ni1000, LG-Ni1000, Pt200 standard, Pt500, Pt1000, PTC: 0.25 mA
Technical unit for temperature measurement adjustable	Yes; °C/°F/K
Input ranges (rated values), voltages	
• 0 to +5 V	No
• 0 to +10 V	No
• 1 V to 5 V	No
• -1 V to +1 V	Yes
— Input resistance (-1 V to +1 V)	10 MΩ
• -10 V to +10 V	No
• -2.5 V to +2.5 V	No
• -25 mV to +25 mV	Yes
— Input resistance (-25 mV to +25 mV)	10 MΩ
• -250 mV to +250 mV	Yes
— Input resistance (-250 mV to +250 mV)	10 MΩ
• -5 V to +5 V	No
• -50 mV to +50 mV	Yes
— Input resistance (-50 mV to +50 mV)	10 MΩ
• -500 mV to +500 mV	Yes
— Input resistance (-500 mV to +500 mV)	10 MΩ
• -80 mV to +80 mV	Yes
— Input resistance (-80 mV to +80 mV)	10 MΩ
Input ranges (rated values), currents	
• 0 to 20 mA	No
• -20 mA to +20 mA	No
• 4 mA to 20 mA	No
Input ranges (rated values), thermocouples	
• Type B	Yes
— Input resistance (Type B)	10 MΩ
• Type C	Yes
— Input resistance (Type C)	10 MΩ
• Type E	Yes
— Input resistance (Type E)	10 MΩ
• Type J	Yes
— Input resistance (type J)	10 MΩ
• Type K	Yes
— Input resistance (Type K)	10 MΩ
• Type L	No
• Type N	Yes
— Input resistance (Type N)	10 MΩ
• Type R	Yes
— Input resistance (Type R)	10 MΩ
• Type S	Yes
— Input resistance (Type S)	10 MΩ
• Type T	Yes
— Input resistance (Type T)	10 MΩ
• Type TXK/TXK(L) to GOST	Yes
— Input resistance (Type TXK/TXK(L) to GOST)	10 MΩ
Input ranges (rated values), resistance thermometer	
• Cu 10	Yes; Standard/climate
— Input resistance (Cu 10)	10 MΩ
• Cu 10 according to GOST	Yes; Standard/climate
— Input resistance (Cu 10 according to GOST)	10 MΩ
• Cu 50	Yes; Standard/climate
— Input resistance (Cu 50)	10 MΩ
• Cu 50 according to GOST	Yes; Standard/climate

— Input resistance (Cu 50 according to GOST)	10 MΩ
• Cu 100	Yes; Standard/climate
— Input resistance (Cu 100)	10 MΩ
• Cu 100 according to GOST	Yes; Standard/climate
— Input resistance (Cu 100 according to GOST)	10 MΩ
• Ni 10	Yes; Standard/climate
— Input resistance (Ni 10)	10 MΩ
• Ni 10 according to GOST	Yes; Standard/climate
— Input resistance (Ni 10 according to GOST)	10 MΩ
• Ni 100	Yes; Standard/climate
— Input resistance (Ni 100)	10 MΩ
• Ni 100 according to GOST	Yes; Standard/climate
— Input resistance (Ni 100 according to GOST)	10 MΩ
• Ni 1000	Yes; Standard/climate
— Input resistance (Ni 1000)	10 MΩ
• Ni 1000 according to GOST	Yes; Standard/climate
— Input resistance (Ni 1000 according to GOST)	10 MΩ
• LG-Ni 1000	Yes; Standard/climate
— Input resistance (LG-Ni 1000)	10 MΩ
• Ni 120	Yes; Standard/climate
— Input resistance (Ni 120)	10 MΩ
• Ni 120 according to GOST	Yes; Standard/climate
— Input resistance (Ni 120 according to GOST)	10 MΩ
• Ni 200	Yes; Standard/climate
— Input resistance (Ni 200)	10 MΩ
• Ni 200 according to GOST	Yes; Standard/climate
— Input resistance (Ni 200 according to GOST)	10 MΩ
• Ni 500	Yes; Standard/climate
— Input resistance (Ni 500)	10 MΩ
• Ni 500 according to GOST	Yes; Standard/climate
— Input resistance (Ni 500 according to GOST)	10 MΩ
• Pt 10	Yes; Standard/climate
— Input resistance (Pt 10)	10 MΩ
• Pt 10 according to GOST	Yes; Standard/climate
— Input resistance (Pt 10 according to GOST)	10 MΩ
• Pt 50	Yes; Standard/climate
— Input resistance (Pt 50)	10 MΩ
• Pt 50 according to GOST	Yes; Standard/climate
— Input resistance (Pt 50 according to GOST)	10 MΩ
• Pt 100	Yes; Standard/climate
— Input resistance (Pt 100)	10 MΩ
• Pt 100 according to GOST	Yes; Standard/climate
— Input resistance (Pt 100 according to GOST)	10 MΩ
• Pt 1000	Yes; Standard/climate
— Input resistance (Pt 1000)	10 MΩ
• Pt 1000 according to GOST	Yes; Standard/climate
— Input resistance (Pt 1000 according to GOST)	10 MΩ
• Pt 200	Yes; Standard/climate
— Input resistance (Pt 200)	10 MΩ
• Pt 200 according to GOST	Yes; Standard/climate
— Input resistance (Pt 200 according to GOST)	10 MΩ
• Pt 500	Yes; Standard/climate
— Input resistance (Pt 500)	10 MΩ
• Pt 500 according to GOST	Yes; Standard/climate
— Input resistance (Pt 500 according to GOST)	10 MΩ

Input ranges (rated values), resistors

• 0 to 150 ohms	Yes
— Input resistance (0 to 150 ohms)	10 MΩ
• 0 to 300 ohms	Yes
— Input resistance (0 to 300 ohms)	10 MΩ

<ul style="list-style-type: none"> • 0 to 600 ohms <ul style="list-style-type: none"> — Input resistance (0 to 600 ohms) • 0 to 3000 ohms • 0 to 6000 ohms <ul style="list-style-type: none"> — Input resistance (0 to 6000 ohms) • PTC <ul style="list-style-type: none"> — Input resistance (PTC) 	<p>Yes</p> <p>10 MΩ</p> <p>No</p> <p>Yes</p> <p>10 MΩ</p> <p>Yes</p> <p>10 MΩ</p>
Thermocouple (TC)	
Temperature compensation	
<ul style="list-style-type: none"> — parameterizable — internal temperature compensation — external temperature compensation via RTD — Compensation for 0 °C reference point temperature — Reference channel of the module 	<p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes; fixed value can be set</p> <p>Yes; 9th channel that can be used as a genuine 9th RTD channel regardless of the parameterization of the other channels, or that can be used for compensation in the case of TC measurement</p>
Cable length	
<ul style="list-style-type: none"> • shielded, max. 	800 m; at U; 200 m at R/RTD/TC
Analog value generation for the inputs	
Integration and conversion time/resolution per channel	
<ul style="list-style-type: none"> • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Integration time (ms) • Basic conversion time, including integration time (ms) <ul style="list-style-type: none"> — additional conversion time for wire-break monitoring • Interference voltage suppression for interference frequency f1 in Hz • Basic execution time of the module (all channels released) 	<p>21 bit; For measuring mode RTC and TC when using the function "Scalable temperature measuring range" (32 bit REAL format); 16 bit for measuring mode R and U; 16 bit for all measuring modes when using the S7 format (16 bit INTEGER)</p> <p>Yes</p> <p>Fast mode: 2.5 / 16.67 / 20 / 100 ms, standard mode: 7.5 / 50 / 60 / 300 ms</p> <p>Fast mode: 4 / 18 / 22 / 102 ms; Standard mode: 9 / 52 / 62 / 302 ms</p> <p>Thermocouples, 150 Ohm, 300 Ohm, 600 Ohm, Cu10, Cu50, Cu100, Ni10, Ni100, Ni120, Ni200, Pt10, Pt50, Pt100: 4 ms; 6 kOhm, Ni500, Ni1000, LG-Ni1000, Pt200, Pt500, Pt1000: 13 ms</p> <p>400 / 60 / 50 / 10 Hz</p> <p>Corresponds to the channel with the highest basic conversion time</p>
Smoothing of measured values	
<ul style="list-style-type: none"> • parameterizable • Step: None • Step: low • Step: Medium • Step: High 	<p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p>
Encoder	
Connection of signal encoders	
<ul style="list-style-type: none"> • for voltage measurement • for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection 	<p>Yes</p> <p>No</p> <p>No</p> <p>Yes</p> <p>Yes; All measuring ranges except PTC; internal compensation of the cable resistances</p> <p>Yes; All measuring ranges except PTC</p>
Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.02 %
Temperature error (relative to input range), (+/-)	0.005 %/K
Crosstalk between the inputs, max.	-80 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.02 %
Temperature error of internal compensation	±1,5 °C
Operational error limit in overall temperature range	
<ul style="list-style-type: none"> • Voltage, relative to input range, (+/-) 	0.1 %

<ul style="list-style-type: none"> Resistance, relative to input range, (+/-) Resistance thermometer, relative to input range, (+/-) Thermocouple, relative to input range, (+/-) 	0.1 % Cuxxx Standard: ±0.5 K, Cuxxx Klima: ±0.5 K, Ptxxx Standard: ±1 K, Ptxxx Klima: ±0.5 K, Nixxx Standard: ±0.5 K, Nixxx Klima: ±0.3 K Type B: > 600 °C ±2 K, Type E: > -200 °C ±1 K, Type J: > -210 °C ±1 K, Type K: > -200 °C ±2 K, Type N: > -200 °C ±2 K, Type R: > 0 °C ±2 K, Type S: > 0 °C ±2 K, Type T: > -200 °C ±1 K, Type C: ±4 K, Type TXK/TXK(L): ±1 K
Basic error limit (operational limit at 25 °C)	
<ul style="list-style-type: none"> Voltage, relative to input range, (+/-) Resistance, relative to input range, (+/-) Resistance thermometer, relative to input range, (+/-) Thermocouple, relative to input range, (+/-) 	0.05 % 0.05 % Cuxxx Standard: ±0.3 K, Cuxxx Klima: ±0.2 K, Ptxxx Standard: ±0.5 K, Ptxxx Klima: ±0.2 K, Nixxx Standard: ±0.3 K, Nixxx Klima: ±0.15 K Type B: > 600 °C ±1 K, Type E: > -200 °C ±0.5 K, Type J: > -210 °C ±0.5 K, Type K: > -200 °C ±1 K, Type N: > -200 °C ±1 K, Type R: > 0 °C ±1 K, Type S: > 0 °C ±1 K, Type T: > -200 °C ±0.5 K, Type C: ±2 K, Type TXK/TXK(L): ±0.5 K
Interference voltage suppression for $f = n \times (f_1 \pm 1 \%)$, $f_1 =$ interference frequency	
<ul style="list-style-type: none"> Series mode interference (peak value of interference < rated value of input range), min. Common mode voltage, max. Common mode interference, min. 	80 dB; in the Standard operating mode, 40 dB in the Fast operating mode 60 V DC/30 V AC 80 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
<ul style="list-style-type: none"> Diagnostic alarm Limit value alarm 	Yes Yes; two upper and two lower limit values in each case
Diagnoses	
<ul style="list-style-type: none"> Monitoring the supply voltage Wire-break Overflow/underflow 	Yes Yes; Only with TC, R, RTD Yes
Diagnostics indication LED	
<ul style="list-style-type: none"> RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics 	Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED
Potential separation	
Potential separation channels	
<ul style="list-style-type: none"> between the channels between the channels, in groups of between the channels and backplane bus between the channels and the power supply of the electronics 	Yes 1 Yes Yes
Permissible potential difference	
between different circuits	60 V DC/30 V AC; insulation rated for 120 V AC basic insulation: between the channels and the supply voltage L+; between the channels and the backplane bus; between the channels
Isolation	
Isolation tested with	2 000 V DC between the channels and the supply voltage L+; 2 000 V DC between the channels and the backplane bus; 2 000 V DC between the channels; 707 V DC (type test) between the supply voltage L+ and the backplane bus
Standards, approvals, certificates	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes; Based on AMS 2750 E
Ambient conditions	
Ambient temperature during operation	
<ul style="list-style-type: none"> horizontal installation, min. horizontal installation, max. vertical installation, min. vertical installation, max. 	0 °C 60 °C 0 °C 40 °C
Dimensions	

Width	35 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	290 g
Other	
Note:	for the R/RDT three-wire measurement, the conductor compensation is made alternating with the measurement; this then requires two module cycles for a measured value

last modified:

4/29/2021 