# **SIEMENS**

### Data sheet

## 3KD3032-2NE10-0



SWITCH-DISCONNECTOR 100A, FRAME SIZE 2, 3-POLE FRONT OPERATING LEFT COMPLETE ASSEMBLY WITH DIRECT HANDLE GREY BOX TERMINAL

Model		
product brand name		SENTRON
Product designation		Switching device
Design of the product		3KD switch disconnectors
Design of the operating mechanism		manual operating mechanism
Design of handle		Direct operating mechanism, gray
Type of the driving mechanism / motor drive		No
General technical data		
Number of poles		3
Type of device		fixed mounting
circuit-breaker / Design		3KD3
Mechanical service life (switching cycles) / typical		15 000
Overvoltage category		Ш
Voltage		
Insulation voltage / Rated value	V	1 000
Surge voltage resistance / Rated value	kV	8
Protection class		
Protection class IP		IP20
Protection class IP / on the front		IP20
Dissipation		
Active power loss		
<ul> <li>with conventional rated thermal current / per</li> </ul>	W	3
pole		

Electricity		
Continuous current		
Rated value	А	100
• at 40 °C / Rated value	А	100
● at 45 °C / Rated value	А	100
● at 50 °C / Rated value	А	100
● at 55 °C / Rated value	А	100
● at 60 °C / Rated value	А	100
● at 65 °C / Rated value	А	100
● at 70 °C / Rated value	А	100
Short-time current resistance (Icw) / limited to 1 s / Rated value	kA	4
Main circuit		
Operating power		
<ul> <li>at AC-23 A / at 400 V / at 50/60 Hz / Rated value</li> </ul>	kW	55
• at AC-23 A / at 500 V / at 50/60 Hz / Rated value	kW	55
• at AC-23 A / at 690 V / at 50/60 Hz / Rated value	kW	90
Operating voltage		
• with AC / at 50/60 Hz / Rated value	V	690
Auxiliary circuit		
Number of CO contacts / for auxiliary contacts		4
Number of NC contacts / for auxiliary contacts		0
Number of NO contacts / for auxiliary contacts		0
Suitability		
Suitability for use		
Main switch		Yes
<ul> <li>switch disconnector</li> </ul>		Yes
<ul> <li>EMERGENCY OFF switch</li> </ul>		No
<ul> <li>safety switch</li> </ul>		Yes
<ul> <li>maintenance/repair switch</li> </ul>		Yes
Product details		
Product feature / interlock		Yes
Product component		
• Trip indicator		No
Voltage trigger		No
<ul> <li>undervoltage release</li> </ul>		No
<ul> <li>undervoltage release with leading contact</li> </ul>		No
Product expansion		


Auxiliary switch		Yes		
• optional				
— motor drive		No		
— Voltage trigger		No		
onnections	_			
Type of electrical connection				
• for main current circuit		Box terminal		
echanical Design				
leight	mm	126		
Vidth	mm	121		
Depth	mm	97		
nounting position		any		
Mounting type		Floor mounting and snap-on mounting to 35 mm standard mounting rail		
Nounting type				
<ul> <li>front mounting with 4-hole attachment</li> </ul>		No		
<ul> <li>front mounting with central attachment</li> </ul>		No		
• rail mounting		Yes		
nvironmental conditions				
Ambient temperature				
<ul> <li>during operation / minimum</li> </ul>	°C	-25		
<ul> <li>during operation / maximum</li> </ul>	°C	70		
<ul> <li>during storage / minimum</li> </ul>	°C	-50		
<ul> <li>during storage / maximum</li> </ul>	°C	80		
ertificates				
Equipment marking / acc. to DIN EN 61346-2		Q		
General Product Approval		Declaration of Conformity		
GOST VDE	EHC	EG-Konf.		
urther information				
Information- and Downloadcenter (Catalogs, Brochures,) http://www.siemens.com/lowvoltage/catalogs				
ndustry Mall (Online ordering system) https://eb.automation.siemens.com/mall/en/WW/Catalog/P	roduct/3KD303	22NE100		
Service&Support (Manuals, Certificates, Characteristics, FAQs,) http://support.automation.siemens.com/WW/view/en/3KD30322NE100/all				


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...) http://www.automation.siemens.com/bilddb/cax\_en.aspx?mlfb=3KD30322NE100


#### CAx-Online-Generator


http://www.siemens.com/cax

Tender specifications http://ausschreibungstexte.siemens.com/tiplv









last modified:

11.03.2015