

Product Search Data Sheet

Note: This datasheet may be out of date

Please download the latest datasheet of BLM18KG700WH1# from the official website of Murata Manufacturing Co., Ltd.

https://www.murata.com/en-us/products/productdetail?partno=BLM18KG700WH1%23

BLM18KG700WH1#

"#" indicates a package specification code.


In Production RoHS REACH AEC-

< List of part numbers with package codes > BLM18KG700WH1J BLM18KG700WH1D BLM18KG700WH1B



Appearance & Shape







The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

BLM BLM Series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 2ADC.

BLM18A_WH series is designed for conductive glue mounting method, not for normal soldering method. Please contact us for applicable mounting method for BLM18A_WH series.

Applications

| Automotive Usage Powertrain/Safety |
|---------------------------------------|
|---------------------------------------|

Packaging Information

| Packaging | Specifications | Minimum Order Quantity |
|-----------|------------------|---------------------------|
| J | 330mm Paper Tape | 10000 |
| D | 180mm Paper Tape | 4000 |
| В | Bulk(Bag) | 1000 |

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



Note: This datasheet may be out of date

Please download the latest datasheet of BLM18KG700WH1# from the official website of Murata Manufacturing Co. 1 td

<u>Co., Ltd.</u> https://www.murata.com/en-us/products/productdetail?partno=BLM18KG700WH1%23

BLM18KG700WH1#

"#" indicates a package specification code.

Specifications

| Shape | SMD | |
|---------------------------------|----------------|--|
| Size Code (in mm) | 1608 | |
| Size Code (in inch) | 0603 | |
| Length | 1.6mm | |
| Length Tolerance | ±0.15mm | |
| Width | 0.8mm | |
| Width Tolerance | ±0.15mm | |
| Thickness | 0.6mm | |
| Thickness Tolerance | ±0.15mm | |
| Impedance (at 100MHz) | 70Ω | |
| Impedance (at 100MHz) Tolerance | ±25% | |
| Rated Current (at 85°C) | 1.65A | |
| Rated Current (at 125°C) | 1.65A | |
| Rated Current (at 150°C) | 1A | |
| DC Resistance(max.) | 0.047Ω | |
| Operating Temperature Range | -55°⊂ to 150°⊂ | |
| Mass(typ.) | 0.004g | |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



Note: This datasheet may be out of date

Please download the latest datasheet of BLM18KG700WH1# from the official website of Murata Manufacturing Co., Ltd.


https://www.murata.com/en-us/products/productdetail?partno=BLM18KG700WH1%23

BLM18KG700WH1#

"#" indicates a package specification code.




INNOVATOR IN FLECT




In operating temperature exceeding +125°C, derating of current is necessary for BLM18KG_WH1 series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics

Derating of Rated Current



Equivalent Circuit

3 of 3

Attention

 This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

