

MIRO, TR, 24VDC, 24VDC 6A SK OPTO-COUPLER MODULE


IN: 53 VDC - OUT: 48 VDC / 6 A

Transistor 6 A 24 V DC Screw terminals

Link to Product

Illustration






The information in this brochure has been compiled with the utmost care. Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/15

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.de | shop.murrelektronik.de



stay connected



Product may differ from Image

Approvals



Input

Input	
Voltage range ON	1053 V DC
Voltage range OFF	05 V DC
Control current	approx. 10 mA
LED display	LED (yellow)
General data	
Test isolation voltage	2.75 kV
Mounting method	DIN-rail mountable (EN 60715)
Housing	Black plastic, flame retardant
Temperature range	-20+60 °C
Dimensions $H \times W \times D$	78×6.2×65 mm
Output	
Switching voltage	548 V DC
Switching current per output	1 mA6 A (without derating)
Saturation voltage (across output)	max. 0.1 V DC
Leakage current (output is open)	max. 25 μA
Switching time ON/OFF	2/5 ms
Switching frequency	max. 1/0.1 Hz (resist./ind.)
Commercial data	
country of origin	CZ
customs tariff number	85414090
minimum order quantity	1

The information in this brochure has been compiled with the utmost care.

Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/15

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.de | shop.murrelektronik.de