## Surface Mount Low Leakage Diode



RoHS Compliant



### **Features**

- · Low leakage current
- · High reverse breakdown voltage
- · Fast switching speed
- · Surface mount package ideally suited for automatic insertion

### **Application**

· Surface mount fast switching diode.

### Maximum Rating @ TA = 25°C unless otherwise specified

Characteristic	Symbol	Value	Unit
Peak Repetitive Reverse Voltage	Vrrm	350	V
Working Peak Reverse Voltage DC Reverse Voltage	V <sub>RWM</sub> V <sub>R</sub>	300	V
RMS Reverse Voltage	VR(RMS)	212	V
Forward Continuous Current	Iғм	225	mA
Repetitive Peak Forward Current	IFRM	625	mA
Non-Repetitive Peak Forward Surge Current @t=1µs @t=1s	Ігѕм	4 1	А
Power Dissipation	Po	400	mW
Thermal Resistance Junction to Ambient Air	RθJA	312	°C/W
Operating and Storage Temperature Rage	ТJ, Tsтg	-65 to +150	°C

### Electrical Characteristics @ TA = 25°C unless otherwise specified

Characteristic	Symbol	Min.	Тур.	Max.	Unit	Test Condition
Reverse Breakdown Voltage	V(BR)R	350	-	-	V	IR = 150μA
			0.78	0.87		IF = 20mA
Forward Voltage	VF		0.93	1	V	IF = 100mA
			1.03	1.25		IF = 200mA
Reverse Current	lr		30	100	nA	VR = 240V, TJ = 25°C
			35	100	μA	VR = 240V, T <sub>J</sub> = 150°C
Total Capacitance	Ст		1	5	pF	V <sub>R</sub> = 0V, f = 1MHz
Reverse Recovery Time	trr		-	50	ns	IF = IR = $30$ mA, Irr = $0.1 \times IR$ ,RL = $100$ Ω


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro





# Surface Mount Low Leakage Diode




## Typical Characteristics @ TA = 25°C unless otherwise specified











#### **Package Outline**

Plastic surface mounted package



SOD-123					
Dim.	Min.	Max.			
Α	1.45	1.75			
В	2.55	2.85			
С	1.15 Typical				
D	0.55 Typical				
Е	0.25	0.45			
Н	0.02	0.1			
J	0.1 Typical				
K	3.55	3.85			

## **Soldering Footprint**



Dimensions: Millimetres

### **Part Number Table**

Description	Part Number	
Signal Diode, Single, 350V, 225mA, 1.25V	BAV3004W-7-F	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

