

#### **General Information**

 Extended Product Type:
 F204 A-40/0,3

 Product ID:
 2CSF204101R3400

 EAN:
 8012542783800

Catalog Description: F204 A-40/0,3 Residual Current Dev.

Long Description: The RCCBs F200 series assures protection to people and installations against fault current

to earth. A large offer for standard instantaneous and selective AC and A types is completed

with some configurations for special applications.

#### Categories

Products » Low Voltage Products and Systems » Modular DIN Rail Products » Residual Current Devices RCDs » Residual Current Devices RCDs

#### **Ordering**

 EAN:
 8012542783800

 Minimum Order Quantity:
 1 piece

 Customs Tariff Number:
 85363030

#### **Dimensions**

Product Net Width:0.070 mProduct Net Height:0.085 mProduct Net Depth:0.069 mProduct Net Weight:0.360 kg

## **Container Information**

 Package Level 1 Units:
 1 piece

 Package Level 1 Width:
 0.082 m

 Package Level 1 Height:
 0.078 m

 Package Level 1 Length:
 0.096 m

 Package Level 1 Gross Weight:
 0.403 kg

 Package Level 1 EAN:
 8012542783800

#### **Technical**

Standards: IFC/FN 61008 UL 1053 Operating Characteristic: Instantaneous Type of Residual Current: A type **Rated Residual Current:** 300 mA Rated Current (In): 40 A **Number of Poles:** 4 **Position of Neutral Terminals:** Right Power Loss: at Rated Operating Conditions per Pole 3.2 W Rated Voltage (U<sub>r</sub>): 230/400 V

### **Environmental**

RoHS Status: Planned to follow EU Directive 2002/95/EC August 18, 2005 and amendment after 2007 Q3

## **Technical UL/CSA**

Maximum Operating Voltage 480Y/277 V AC UL/CSA:

## **Certificates and Declarations (Document Number)**

 Data Sheet, Technical Information:
 2CSC400002D0209

 Declaration of Conformity - CE:
 2CSC423001D2701

 RoHS Information:
 2CSC423001K0201

 Instructions and Manuals:
 2CSF423001D6402

## Classifications

Object Classification Code:	Q
E-nummer:	2160130
ETIM 4:	EC000003 - Residual current circuit breaker (RCCB)
ETIM 5:	EC000003 - Residual current circuit breaker (RCCB)

# ETIM 6:

