

Accessories from Tufvassons

Tufvassons offers over 2,500 transformers as well as accessories of various kinds. Don't hesitate to contact us for further information about more accessories and guidance for the correct power supply.



Cable for SELV voltage

The cable is 3 m long and fits transformers with AMP socket, including PFS 7S, PFS 20S, PFS 61S and PFLF 12S. One end is equipped with end sleeves on the conductors and the other end has a plug with locking that fits 2-pole polarized AMP sockets.

Part. no.: 2430-3121 length 3 m E 52 001 47

Max. voltage: 50 V

Load: As per table, though not over 2.5 A

Weight: 340 g

Design: - Cable 2x0.5 mm². One end has end sleeves on the conductors and the other end a plug with locking suitable for 2-pole polarized AMP socket.

Max. length of cable at different loads:

Light	Current	max. length
12V 10W	0.83 A	10 m
12V 20W	1.67 A	5 m
12V 30W	2.50 A	3.5 m
24V 10W	0.42 A	30 m
24V 20W	0.83 A	20 m
24V 30W	1.25 A	15 m
24V 40W	1.67 A	10 m
24V 60W	2.50 A	7 m

The secondary voltage drop must never exceed:

at 12V 0.6V

at 24V 1.0V

Suitable for PFS 7S, PFS 20S, PFS 61S and PFLF 12S with AMP socket.



12/12



Tufvassons Transformator AB · Märstavägen 20 · 193 40 Sigtuna · Phone +46 (0) 8 594 809 00
Fax +46 (0) 8 592 527 68 · E-mail reception@tufvassons.se · www.tufvassons.se

A company in the ADDTECH group.