
Transient Voltage Suppression Diodes P6KE Series, 600W





Features

- · Exceeds environmental standards of MIL-STD-19500
- 600W surge capability at 10 × 1,000µs waveform, duty cycle: 0.01%
- · Excellent clamping capability
- · Low zener impedance
- Fast response time: typically less than 1ps from 0V to VBR for unidirectional and 5ns for bidirectional
- Typical IR less than 1µA above 10 V
- High temperature soldering guaranteed: 260°C / 10 seconds / 0.375 Inched (9.5mm) lead length/5lbs. (2.3kg) tension
- · Case style: DO-204AC (DO-15) molded plastic

Mechanical Data


Case : Molded plastic

Lead : Pure tin plated lead free, solderable per MIL-STD-202, Method 208

Polarity: Colour band denotes cathode except bipolar

Weight: 0.42g

RoHS Compliant



Dimensions : Inches (Millimetres)

Maximum Ratings and Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60Hz, resistive or inductive load.

For capacitive load, derate current by 20%.

Characteristics	Symbol	Values	Unit
Peak Power Dissipation at T _A = 25°C, T _P = 1ms (Note 1)	Ррк	Min. 600	
Steady State Power Dissipation at T _L = 75°C Lead Lengths 0.375 Inch 9.5 mm (Note 2)	Po	5	Watts
Peak Forward Surge Current, 8.3ms Single Half Sine-wave Superimposed on Rated Load (JEDEC method) (Note 3)	İFSM	100	Amps
Maximum Instantaneous Forward Voltage at 50A for Unidirectional Only (Note 4)	VF	3.5 / 5	Volts
Operating and Storage Temperature Range	ТJ, Tsтg	-55 to +175	°C

Notes : 1. Non-repetitive current pulse ,per Fig. 5 and derated above $T_A = 25^{\circ}C$ per Fig. 1 .

2. 8.3ms single half-wave duty cycle = 4 pulses per minutes maximum (uni-directional units only).

3. VF = 3.5V on P6KE6.8 thru P6KE130 devices and VF = 5V on P6KE220A thru P6KE400A devices.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Transient Voltage Suppression Diodes P6KE Series, 600W



Ratings and Characteristic Curves

FIG.1-PULSE DERATING CURVE




FIG.3-PULSE RATING CURVE





FIG.2-TYPICAL JUNCTION CAPACITANCE



REVERSE VOLTAGE, VOLTS





FIG.5 -PULSE WAVE FORM



Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Transient Voltage Suppression Diodes P6KE Series, 600W



Electrical Characteristics (TA = 25°C unless otherwise noted)

Part N	umber	Reverse Standoff Voltage		Breakdown Voltage V Lolts @ It	t	Max. Reverse Leakage @	Max. Clamping Voltage @IP	Max. Peak Pulse Current	Max. Voltage Temp. Variation of BV
Unidirectional	Bidirectional	VR(V)	Min. (V)	Max. (V)	It (mA)	IR(μA)	Vc(V)	lpp(A)	% / °C
P6KE6.8A	P6KE6.8CA	5.8	6.45	7.14	10	1000	10.5	57	0.057
P6KE43A	P6KE43CA	36.8	40.9	45.2	1	5	59.3	10.1	0.101
-	P6KE56CA	47.8	53.2	58.8	1	5	77	7.8	0.103
P6KE130A	P6KE130CA	111	124	137	1	5	179	3.3	0.107

Notes:

Suffix'C' denotes bidirectional device . Suffix'A' denotes 5% tolerance device. No suffix denotes 10% tolerance devive.

1. For bidirectional devices having VR of 10volts and under ,the IR limit is doubled .

Part Number Table

Description	Part Number	
TVS Diode, 600W, 6.8VBR Nom, Unidirectional, DO-204AC (DO-15)	P6KE6.8A	
TVS Diode, 600W, 6.8VBR Nom, Bidirectional, DO-204AC (DO-15)	P6KE6.8CA	
TVS Diode, 600W, 43VBR Nom, Unidirectional, DO-204AC (DO-15)	P6KE43A	
TVS Diode, 600W, 43VBR Nom, Bidirectional, DO-204AC (DO-15)	P6KE43CA	
TVS Diode, 600W, 56VBR Nom, Bidirectional, DO-204AC (DO-15)	P6KE56CA	
TVS Diode, 600W, 130VBR Nom, Unidirectional, DO-204AC (DO-15)	P6KE130A	
TVS Diode, 600W, 130VBR Nom, Bidirectional, DO-204AC (DO-15)	P6KE130CA	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

