
## NPN Silicon Planar Transistor 40VCEO, 0.7A Ic

# multicomp PRO



### RoHS Compliant

NPN



#### **Absolute Maximum Ratings**

Description	Symbol	Value	Unit
Collector Emitter Voltage	VCEO	40	V
Collector Base Voltage	Vсво	60	V
Emitter Base Voltage	Vebo	5	V
Collector Current Continuous	lc	0.7	А
Power Dissipation at T <sub>A</sub> = 25°C Derate above 25°C	PD	5 28.6	W mW/°C
Operating and Storage Junction Temperature Range	Tj, Tstg	- 65 to +200	°C
Lead Temperature 1/16", ±1/32" from Case for 10s	T∟	+235	°C
Thermal Resistance			
Junction to Case	Rth(j-c)	35	°C/W

### Electrical Characteristics: (T<sub>A</sub> = +25°C Unless otherwise specified)

Description	Symbol	Test Conditions	Value	Unit
Collector Emitter Voltage	VCEO	Ic = 1mА, Iв = 0	>40	V
Collector Emitter Voltage	VCER	Ic = 1mA, R <sub>BE</sub> = 10Ω	>50	V
Collector Base Voltage	Vсво	Ic = 100μA, IE = 0	>60	V
Emitter Base Voltage	Vebo	Iε = 100μΑ, Ic = 0	>5	V
Collector Cut off Current	ICEX	Vce = 30V, Ie = 0, VBE (off) = 1.5V	<250	nA
DC Current Gain	*hFE	Ic = 150mA, Vce = 2.5V Ic = 150mA, Vce = 10V	>25 50 - 250	
Collector Emitter Saturation Voltage	*VCE(Sat)	Ic = 150mA, Iв = 15mA	<1.4	V
Base Emitter Saturation Voltage	*VBE(Sat)	Ic = 150mA, Iв = 15mA	<1.7	V
Base Emitter On Voltage	*VBE(On)	Ic = 150mA, Vce = 2.5V	<1.7	V
Small Signal Characteristics				
Current Gain Bandwidth Product	f⊤	Ic = 50mA, Vce = 10V, f = 20MHz	>100	MHz
Output Capacitance	Cob	Vсв = 10V, IE = 0, f = 140kHz	<15	pF
Input Capacitance	Cib	VEB = 0.5V, Ic = 0, f = 140kHz	<80	pF

Page <1>


\*Pulse Test: Pulse Width < 300 $\mu$ s, Duty Cycle ≤ 2%

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



## multicomp PRO

#### TO-39 Metal Can Package



Dim.	Min.	Max.
Dim.	IVIIII.	IVIAX.
A	8.5	9.39
В	7.74	8.5
С	6.09	6.6
D	0.4	0.53
E	-	0.88
F	2.41	2.66
G	4.82	5.33
Н	0.71	0.86
J	0.73	1.02
К	12.7	-
L	42 Deg.	48 Deg.

**Dimensions : Millimetres** 

#### Part Number Table

Description	Part Number	
NPN Silicon Planar Transistor, 40V, 0.7A, TO-39	MP001169	

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

