

Product Search Data Sheet

BLM15PX601SZ1D

Please download the latest datasheet of BLM15PX601SZ1# from the official website of Murata Manufacturing Co., Ltd.
http://www.murata.com/en/products/productdetail?partno=BLM15PX601SZ1%23

Note: This datasheet may be out of date.

"#" indicates a package specification code.


In Production AEC-Q200 RoHS REACH

< List of part numbers with package codes > BLM15PX601SZ1J BLM15PX601SZ1B BLM15PX601SZ1D



Appearance & Shape









0.5±0.05	

Electrode :

Packaging	Information

Packaging	Specifications	Standard Packing Quantity
J	330mm Paper Tape	50000
В	Bulk(Bag)	1000
D	180mm Paper Tape	10000

Applications

Automotive Usage

Infotainment

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Product Search Data Sheet

BLM15PX601SZ1D

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15PX601SZ1%23

"#" indicates a package specification code.



Features

- 1. The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance. 3.BLM_P series can be used in high current circuits
- due to its low DC resistance. It can match power lines to a maximum of 6ADC.

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

- without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.





Rata Product Search Data Sheet

BLM15PX601SZ1D

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15PX601SZ1%23

"#" indicates a package specification code.



Specifications

Shape	SMD
Size Code (in inch)	0402
Length	1.0mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.5mm
Thickness Tolerance	±0.05mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.001g
Number of Circuit	1
Rated Current (at 85°C)	900mA
Rated Current (at 125°C)	500mA
DC Resistance(max.)	0.23Ω
Impedance (at 100MHz)	600Ω
Impedance (at 100MHz) Tolerance	±25%
Size Code (in mm)	1005

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



Product Search Data Sheet


BLM15PX601SZ1D

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15PX601SZ1%23


"#" indicates a package specification code.

Product Data



In operating temperature exceeding +85°C, derating of current is necessary for BLM15PX series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Derating of Rated Current

(Resistance element becomes dominant at high frequencies.)

Impedance-Frequency Characteristics

Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

