



ESD Handbook TR20.20 Table 1 lists under Typical Static Electricity Sources "Brushes (camel/pig hair and synthetic bristles)." "It should be understood that any object, item, material or person could be a source of static electricity in the work environment. Removal of unnecessary nonconductors, replacing nonconductive materials with dissipative or conductive materials and grounding all conductors are the principle methods of controlling static electricity in the workplace, regardless of the activity." (TR 20.20 section 2.4)

Features:

- ESD Brushes are ideal for removing dust, dirt, and left over materials from printed circuit boards (PCB) and other static senstive components
- Brushes minimize static charge generation and remove electrostatic charges to ground when held by grounded personnel
- Volume Resistance of Conductive Fibers:
 1 x 10³ to < 1 x 10⁵ ohms tested per ANSI/ESD STM 11.12
- Bristle Material: Black conductive nylon
- Length: 6-3/4" (171mm)
 Brush Width: 2" (51mm)
 Bristle Firmness: Soft
- · Handle Material: Conductive black polypropylene

Made in Israel

Unless otherwise noted, tolerance is ±10%.

Specifications and procedures subject to change without notice.

MENDA

ESD BRUSH, CONDUCTIVE, FLAT HANDLE, BLACK SOFT NYLON BRISTLES, 2 IN

3651 WALNUT AVE., CHINO, CA 91710

PHONE: (909) 627-2453 WEBSITE: MendaPump.com DRAWING NUMBER 36092 **DATE:**December 2017