
Bipolar Transistor





RoHS Compliant



Description:

Silicon TO-126 PNP Power Transistor for use in power amplifier and switching excellent safe area limits.

Absolute Maximum Ratings:

Characteristic	Symbol	Rating
Collector - Base Voltage	Vсво	40V
Collector - Emitter Voltage	VCEO	40V
Emitter - Base Voltage	Vево	5V
Continuous Collector Current	Ic	4A
Base Current	Ів	1A
Total Device Dissipation (Tc = +25°C) Derate above 25°C	Po	36W 320mW/°C
Operating Junction Temperature Range	TJ	-65°C to +150°C
Storage Temperature Range	Тsтg	-65°C to +150°C

Electrical Characteristics (TA = 25°C unless otherwise specified)

Parameter	Symbol	Test Conditions	Min.	Max.	Unit
OFF Characteristics			•	,	
Collector - Emitter Breakdown Voltage (Note1)	V(BR)CEO	Ic = 0.1A, I _B = 0	40	-	V
	ICEX	Vce = 40V, VeB(off) = 1.5V	-	0.1	mA
Collector Cut-off Current	Ісво	V _{CB} = 40V, I _E = 0	-	0.1	mA
	ICEO	V _{CB} = 40V, I _B = 0	-	1	mA
Emitter Cut-off Current	IEBO	V _{EB} = 5V, I _C = 0	-	1	mA
ON Characteristics (Note 1)				•	
DC Current Gain	hFE	Vce = 2V, Ic = 1.5A	25	100	-
DC Current Gain	IIFE	$V_{CE} = 2V$, $I_{C} = 4A$	10	-	-
Collector Emitter Saturation Voltage	Vce(sat)	Ic = 1.5A, I _B = 0.15A	-	0.6	V
Collector - Emitter Saturation Voltage		Ic = 4A, I _B = 1A	-	1.4	V
Base - Emitter On Voltage	VBE(on)	Ic = 1.5A VcF = 2V	_	12	V

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro




Bipolar Transistor



Parameter	Symbol	Test Conditions	Min.	Max.	Unit
Small-Signal Characteristics					
Current Gain - Bandwidth Product (Note 2)	f _T	Vce = 10V, Ic = 1A, f = 1MHz	2	-	MHz

Note 1 : Pulse test : Pulse width \leq 300 μ s, Duty Cycle \leq 1.5%

Note 2: f_T is defined as the frequency at which $|h_{fe}|$ extrapolates to unity.



Pin Configuration:

- 1. Emitter
- 2. Collector
- 3. Base

Dim.	Min.	Max.
Α	10.8	11.05
В	7.49	7.75
С	2.41	2.67
D	0.51	0.66
F	2.92	3.18
G	2.31	2.46
Н	1.27	2.41
J	0.38	0.64
K	15.11	16.64
М	3° .	TYP
Q	3.76	4.01
R	1.14	1.4
S	0.64	0.89
U	3.68	3.94
V	1.02	-

Dimensions : Millimetres

Part Number Table

Description	Part Number		
Bipolar Transistor, PNP, 1A, 40V, TO-126	2N5193		

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

