



## Signalling switch ON-OFF, 2W

Part no. IZMX-AS22-40-1  
 Article no. 184115  
 Catalog No. 67C2823G92

### Delivery programme

Product range			Accessories
Accessories			Auxiliary contact
Accessories			Standard auxiliary switch for On-Off signaling
			The basic device already contains two changeover contacts. Mounting kit with 2 additional changeover contacts with cable lengths for IZMX40.
For use with			IZMX40... INX40...
Instructions			Retrofit kit for IZMX40 circuit-breakers For retrofitting, three additional control circuit terminal units are required. For fixed mounting circuit-breakers → #156593 and withdrawable unit circuit-breakers → #156590
			2 changeover contacts

### Technical data

#### Rated breaking capacity

Inductive load			
250 V AC		A	10
125 V DC		A	0.5
250 V DC		A	0.25

### Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

### Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ec1@ss8.1-27-37-13-02 [AKN342010])			
Number of contacts as change-over contact			2
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Rated operation current I <sub>e</sub> at AC-15, 230 V		A	10
Type of electric connection			Flat plug-in connection
Model			Half-integrated
Mounting method			-