



ELECTRONICS

32 RANICK ROAD • HAUPPAUGE, N.Y. 11788-4295
PHONE: (631) 582-3400 FAX: (631) 582-3229
www.mgelectronics.com • e-mail: mgelec@spec.net



SWITCHING POWER SUPPLIES WITH SCREW TERMINALS



LED
Indicator



Features:

- 12V DC Operation
- 100-240V Operation
- Two Screw Terminal Outputs
- LED Supervised
- Energy Efficiency Level IV
- Regulated
- Ultra Lightweight
- Dimensions: 2" x 3¼" x 1½"

Protections:

- Short Circuit Protection
- Over Circuit Protected
- Over Voltage Protected
- cULus Listed, FCC Approved

Model:	Output Voltage:	Input Voltage:	Amperage:	Rated Frequency:	Rated Power:	Weight:	Approvals:
ST-12500	12VDC	100-240V	500mA	50/60 Hz	6 W	3 oz.	UL,cUL,FCC
ST-121A	12VDC	100-240V	1,000mA	50/60 Hz	12 W	3.6 oz.	UL,cUL,FCC
ST-122A	12VDC	100-240V	2,000mA	50/60 Hz	24 W	4.7 oz.	UL,cUL,FCC
ST-241A	24VDC	100-240V	1,000mA	50/60 Hz	12 W	3.6 oz.	UL,cUL,FCC