## **SIEMENS**

Data sheet	6GK6050-0AL20-0FC0
Product type designation	RUGGEDCOM RX5000PN LM 4CG01 LINE MODULE 4X 10/100/1000TX RJ45
Suitability for operation	RX5000
nterfaces	
Number of electrical/optical connections / for network components or terminal equipment / maximum	4
Number of electrical connections	
<ul><li>for network components or terminal equipment / maximum</li></ul>	4
Number of 10/100/1000 Mbit/s RJ45 ports	4
Type of electrical connection	
• for network components or terminal equipment	RJ45
Permitted ambient conditions	
Ambient temperature	
<ul><li>during operation</li></ul>	-40 +85 °C
during storage	-40 +85 °C
during transport	-40 +85 °C
• Note	A maximum ambient operating temperature of +85 °C is permissible for a duration of 16 hours
Relative humidity / at 25 °C / without condensation /	95 %
during operation / maximum	
Protection class IP	IP40
Design, dimensions and weight	
Design	Media module
Width	40 mm
Height	180 mm
Depth	240 mm
Net weight	1 kg
Coating	no
Mounting type	screwed
<ul> <li>Installation in media module slot</li> </ul>	Yes
Standards, specifications, approvals	
Standard	
• for EMC	FCC Part 15 (Class A), EN55022 (CISPR22 Class A)
<ul><li>for safety / from CSA and UL</li></ul>	UL 60950-1, CSA C22.2 No. 60950-7
<ul><li>for hazardous zone / from CSA and UL</li></ul>	Hazardous Locations: Class 1 Division 2

• for emitted interference

EN 61000-6-4 (Class A)

• for interference immunity EN 61000-6-2 Certificate of suitability EN 61000-6-2, EN 61000-6-10 Yes • CE marking • C-Tick No KC approval No • E1 approval No Yes • Railway application in accordance with EN 50155 • Railway application in accordance with EN Yes 50124-1 Yes • IEC 61850-3

## Further Information / Internet Links

## Internet-Link

• to website: Industry Mall/RUGGEDCOM selector

• to website: Siemens RUGGEDCOM

• to website: Selector for cables and connectors

• to website: Industrial communication

• to website: Industry Mall

• to website: Information and Download Center

• to website: Image database

• to website: CAx Download Manager

• to website: Industry Online Support

http://ruggedcom-selector.automation.siemens.com

http://siemens.com/ruggedcom

http://www.siemens.com/snst

http://www.siemens.com/simatic-net

https://mall.industry.siemens.com

http://www.siemens.com/automation/net/catalog

http://automation.siemens.com/bilddb

http://www.siemens.com/cax

https://support.industry.siemens.com

**last modified:** 16.03.2015