DCR 200i



Housing hoods to be used as a replacement in the event of changed operating conditions or as a replacement for defective or scratched original hood

- Housing hoods with either plastic or glass screen (optionally with polarization filter)
- Diffusor foil for increased scatter of the integrated LED illumination of the code reader

Remarks

Operate in accordance with intended use!

- The product may only be put into operation by competent

Order guide

| Haveing band with | Doolgilation | i di t iio. |
|---|--|----------------------------------|
| Housing hood with | | |
| Plastic screen Glass screen Glass screen and polarization filter | Cover DCR 200i Cover DCR 200i-G Cover DCR 200i-P | 50131462 50131461 50131460 |
| Diffusor foil For the screen of the housing hood | Diffusor DCR 200i | 50131459 |

Designation

Part no

Accessories - housing hoods, diffusor foil


Replacing the housing hood

Cover DCR 200i...



Only replace the housing hood while there is no voltage in the system! Clean the new hood with a soft cloth before installing.

Make certain that the sealing surface in the housing base is clean before installing! Tightening torque of the fastening screws < 25 Ncm!



- Loosen the four fastening screws of the housing hood.
- First tip the housing hood downward and away from the housing. **(2)**
- (3) Next lift the housing hood upward.

Then mount the new housing hood in the reverse order ((3), (2), (1)).

Attaching the diffusor foil

Diffusor DCR 200i...



The diffusor foil (50131459) is not suitable for use in combination with the polariza-

Before attaching the foil, make certain that the surface is free of dust and grease! When attaching the diffusor foil, take care to prevent bubbles from forming under the film!

(2)













- Make certain that the diffusor foil is correctly oriented (small opening at top, large opening at bottom).
- Attach the foil to the housing screen from bottom to top.