## **Wirewound Resistor**

# multicomp

### RoHS Compliant




#### Features:

- Derating Linearly from 100% @ +25"C to 0% @ +350"C
- Dielectric withstanding voltage (Measured from terminal to mounting bracket) 25W, 50W, 100W : 1,000V CA 225W : 3,000V CA

#### **Specifications:**


Coating	: Lead free vitreous enamel				
Core	: Tubular Ceramic				
Terminals	: solder-coated radial lug				
Power Rating	: Based on 25°C free air rating				
Overload	: 10 times rated wattage for 5 sec				
Temperature Coefficient	: 1Ω to 20Ω : ±400 ppm/°C				



www.element14.com www.farnell.com www.newark.com







Part Number	Resistance Ω ±5%	Wattage (W)	L	D	С	T1	T2	Dia.	Mounting Bracket Type#	
MC14655	10	25	25	2	0.562	0.212	0.25	0.563	0.166	
MC14656	25		2	0.563	0.313	±0.031 ± 0	± 0.031	±0.015	MC14689	
MC14664	25	50	4	0.563	0.313	0.25 ±0.031	0.563 ± 0.031	0.166 ±0.015		
MC14678	2 5	225	10.5	1.125	0.75	0.375	0.625	0.173	MC14691	
MC14679		225	10.5	1.120	0.75	±0.031	± 0.031	+0.015 -0.005	WC 14091	

#### Part Number Table

Description	Part Number		
Resistor, 10Ω 25W	MC14655		
Resistor, 25Ω 25W	MC14656		
Resistor, 25Ω 50W	MC14664		
Resistor, Power Ceramic, 225W, 2R	MC14678		
Resistor, Power Ceramic, 225W, 5R	MC14679		

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

