## Product data sheet Characteristics

## XEAB25361

booted pushbutton - for control circuit - analog output - 0..15 V DC



TTTOTT		.⊇.
Range of product	Harmony XAC	plicat
Product or component type	Booted push-button	
Control station name	XACB XACM	
Electrical circuit type	Control circuit	for sp
[Us] rated supply voltage	015 V	lucts
Control circuit type	DC	9
Operating travel	11 mm	these.

## Complementary

Contacts type and composition	1 NC + 1 NO at start of travel 1 NO at end of travel	
Current consumption	< 15 mA	
Connections - terminals	Terminal connectors, connection capacity: 1 x 2.5 mm <sup>2</sup> Terminal connectors, connection capacity: 2 x 1.5 mm <sup>2</sup>	
Operating force	4 N at start of travel 9 N at end of travel	
Mechanical durability	1000000 cycles	
[Ithe] conventional enclosed thermal current	6 A	
[Ui] rated insulation voltage	250 V, degree of pollution 3 conforming to IEC 60947-1	
Rated power in VA	30 VA AC-15 for 1000000 cycles at 110 V 50/60 Hz conforming to IEC 60947-5-1 appendix C 30 VA AC-15 for 1000000 cycles at 230 V 50/60 Hz conforming to IEC 60947-5-1 appendix C 30 VA AC-15 for 1000000 cycles at 48 V 50/60 Hz conforming to IEC 60947-5-1 appendix C	
Rated power in W	12 W DC-13 for 1000000 cycles at 110 V, load inductive conforming to IEC 60947-5-1 appendix C 48 W DC-13 for 1000000 cycles at 48 V, load inductive conforming to IEC 60947-5-1 appendix C	
Product weight	0.065 kg	

## Environment

Environment		Ita
Standards	EN 60947-5-1	
	IEC 60947-5-1	досп
Ambient air temperature for operation	-2570 °C	This
Ambient air temperature for storage	-4070 °C	
IP degree of protection	IP65 conforming to IEC 60529	)iscla

Warranty period

18 months