Bridge Rectifier Diode





Features

- · Glass passivated
- · Surge overload rating -60 amperes peak
- · Ideal for printed circuit board
- Reliable low cost construction utilizing moulded plastic technique results in expensive product
- · Mounting position: Any
- · Lead: Sliver plated copper lead

RoHS Compliant

Specifications

Reverse Voltage : 400 Volts Forward Current : 2 Amperes


Max. Ratings and Electrical Characteristics


Rating at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.


Characteristics	Symbol	Values	Unit
Max. Recurrent Peak Reverse Voltage	VRRM	400	
Max. RMS Bridge Input Voltage	VRMS	280	V
Max. DC Blocking Voltage	VDC	400	
Max. Average Forward Rectified Current at T _A = 25°C	I _(AV)	2	А
Peak Forward Surge Current, 8.3ms Single Half Sine-wave Super Imposed on Rated Load	IFSM	60	
I ² t Rating for Fusing (t < 8.3 ms)	l ² t	15	A ² s
Max. Forward Voltage Drop Per Element at 2A Peak	VF	1.1	V
Maximum Reverse Current at Rated T _J = 25°C DC Blocking Voltage T _J = 100°C	lR	10 1	μA mA
Typical Junction Capacitance Per Element (Note 1)	Сл	30	pF
Operating Temperature Range	TJ	55 to 1450	°C
Storage Temperature Range	Тѕтс	-55 to +150	C

Note

Rating and Characteristics Curves







29/10/19 V1.0


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro




^{1.} Measured at 1MHz and applied reverse Voltage of 4V DC


Bridge Rectifier Diode







Diagram



Dimensions: Inches (Millimetres)

Part Number Table

Description	Part Number	
Bridge Rectifier Diode, Single Phase, 400V, 2A	2W04MG	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

