



Sikringskassett, Lav spenning, 250 A, AC 500 V, 120 kA, NH1, gL/gG, IEC, dual indikator, isolerte gripehåndtak



Type **NH FUSE 250A 500V GL/GG SIZE 1**
 Catalog No. **250NHG1BI**

Leveringsprogram

| | | | |
|--|---|----|--|
| Produktspekter | | | Smeltesikring |
| Basisfunksjon | | | Sikringskassett |
| Bruksområde | | | Lav spenning |
| Nominell strøm | I | A | 250 |
| Nominell spenning | | | AC 500 V |
| Konstruksjonsstørrelse | | | NH1 |
| Brukskategori | | | gL/gG |
| Statusindikator | | | dual indikator |
| Beskrivelse | | | isolerte gripehåndtak |
| Bryteevne | | kA | 120 |
| kan brukes for størrelse/applikasjoner | | | industriell |
| Standard/Godkjenning | | | IEC |
| Form | | | firkantet med knivbladkontakter som flukter i endene |
| Standarder/Regulations | | | IEC 60269-2 smeltesikringsystem A DIN 43620 VDE 0636-2 |

Tekniske data etter ETIM 6.0

| | | | |
|--|--|---|---|
| Circuit breakers and fuses (EG000020) / Low Voltage HRC fuse (EC000055) | | | |
| Electric engineering, automation, process control engineering / Electrical installation, device / Safety fuse inserts / Low-Voltage HRC fuse (ecl@ss8.1-27-14-20-05 [AFZ800012]) | | | |
| Construction size | | | NH1 |
| Nominal rated current | | A | 250 |
| Nominal rated voltage | | V | 500 |
| Utilization category | | | gL/gG (cable protection/equipment protection) |
| Type of fuse status indicator | | | Combination fuse status indicator |