## **SIEMENS**

Data sheet 3RH2911-1HA12



AUX.SWITCH BLOCK,FRONT,1NO+2NC, CURR.PATH: 1NC, 1NC, 1NO, F. CONT. RELAYS A. MOTOR CONT., 3RT2 SCREW TERMINAL .1 / .2, .1 / .2, .3 / .4

| General technical data:   |    |  |
|---|----|--|
| product brand name  |    | SIRIUS   |
| Suitability for use   |    | Contactor relay and power contactor  |
| Protection class IP on the front                                  |    | IP20   |
| Ambient temperature   |    |  |
| <ul> <li>during storage</li> </ul>                                | °C | -55 <b>+</b> 80  |
| <ul><li>during operation</li></ul>                                | °C | -25 +60  |
| Mechanical service life (switching cycles) typical                |    | 10 000 000   |
| Electrical endurance (switching cycles) at AC-15 at 230 V typical |    | 200 000  |
| Contact reliability   |    | one incorrect switching operation of 100 million switching operations (17 V, 1 mA) |
| Contact reliability of the auxiliary contacts                     |    | 1 faulty switching per 100 million (17 V, 1 mA)                                    |
| Insulation voltage with degree of pollution 3 Rated value         | V  | 690  |
| Surge voltage resistance Rated value                              | kV | 6  |

| Auxiliary circuit:                                   |   |    |
|--|---|----|
| Number of NC contacts for auxiliary contacts         |   |    |
| • instantaneous contact                              |   | 2  |
| <ul> <li>lagging switching</li> </ul>                |   | 0  |
| Number of NO contacts for auxiliary contacts         |   |    |
| • instantaneous contact                              |   | 1  |
| leading contact                                      |   | 0  |
| Operating current of the auxiliary contacts at AC-12 |   |    |
| ● at 24 V  | Α | 10 |

| ● at 230 V  | Α | 10   |
|---|---|------|
| • maximum   | Α | 10   |
| Operating current   |   |      |
| <ul> <li>of the auxiliary contacts</li> </ul>               |   |      |
| — at AC-14  |   |      |
| — at 125 V  | Α | 6    |
| — at 250 V  | Α | 6    |
| — at AC-15  |   |      |
| — at 24 V   | Α | 6    |
| — at 230 V  | Α | 6    |
| — at 400 V  | Α | 3    |
| • at AC-15 at 690 V Rated value                             | Α | 1    |
| Operating current   |   |      |
| <ul><li>with 2 current paths in series at DC-12</li></ul>   |   |      |
| — at 24 V Rated value                                       | Α | 10   |
| — at 60 V Rated value                                       | Α | 10   |
| — at 110 V Rated value                                      | Α | 4    |
| — at 220 V Rated value                                      | Α | 2    |
| — at 440 V Rated value                                      | Α | 1.3  |
| — at 600 V Rated value                                      | Α | 0.65 |
| <ul> <li>with 3 current paths in series at DC-12</li> </ul> |   |      |
| — at 24 V Rated value                                       | Α | 10   |
| — at 60 V Rated value                                       | Α | 10   |
| — at 110 V Rated value                                      | Α | 10   |
| — at 220 V Rated value                                      | Α | 3.6  |
| — at 440 V Rated value                                      | Α | 2.5  |
| — at 600 V Rated value                                      | Α | 1.8  |
| Operating current   |   |      |
| <ul> <li>of the auxiliary contacts at DC-13</li> </ul>      |   |      |
| — at 24 V   | Α | 6    |
| — at 60 V   | Α | 2    |
| — at 110 V  | Α | 1    |
| — at 220 V  | Α | 0.3  |
| • with 2 current paths in series at DC-13                   |   |      |
| — at 24 V Rated value                                       | Α | 10   |
| — at 60 V Rated value                                       | Α | 3.5  |
| — at 110 V Rated value                                      | Α | 1.3  |
| — at 220 V Rated value                                      | Α | 0.9  |
| — at 440 V Rated value                                      | Α | 0.2  |
| — at 600 V Rated value                                      | Α | 0.1  |
| • with 3 current paths in series at DC-13                   |   |      |

| — at 24 V Rated value  | Α | 10   |
|------------------------|---|------|
| — at 60 V Rated value  | Α | 4.7  |
| — at 110 V Rated value | Α | 3    |
| — at 220 V Rated value | Α | 1.2  |
| — at 440 V Rated value | Α | 0.5  |
| — at 600 V Rated value | Α | 0.26 |

| Installation/ mounting/ dimensions: |    |                  |
|-------------------------------------|----|------------------|
| Mounting type                       |    | snap-on mounting |
| Width                               | mm | 36               |
| Height                              | mm | 37.5             |
| Depth                               | mm | 43.7             |

| Connections/ Terminals:                                       |                                     |
|---|-------------------------------------|
| Type of electrical connection for auxiliary and control       | screw-type terminals                |
| current circuit   |                                     |
| Type of connectable conductor cross-section                   |                                     |
| <ul><li>for auxiliary contacts</li></ul>                      |                                     |
| — finely stranded   |                                     |
| <ul> <li>— with core end processing</li> </ul>                | 2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²) |
| <ul> <li>for AWG conductors for auxiliary contacts</li> </ul> | 2x (20 16), 2x (18 14)              |

| Safety related data:   |           |
|--|-----------|
| Product function Mirror contact acc. to IEC 60947-4-1              | Yes       |
| ● Note   | with 3RT2 |
| Product function positively driven operation acc. to IEC 60947-5-1 | Yes       |
| • Note   | with 3RH2 |

## Certificates/ approvals:

## **General Product Approval**

Declaration of Conformity

Test Certificates











Special Test Certificate

Test Certificates **Shipping Approval** 

Type Test
Certificates/Test

Report









GL



LRS

**Shipping Approval** 

other







Environmental Confirmations



Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system)

http://www.siemens.com/industrymall


Cax online generator


http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RH29111HA12

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)


http://support.automation.siemens.com/WW/view/en/3RH29111HA12/all

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/index.aspx?attlD9=3RH29111HA12&lang=en









## 3RH2

