# DATASHEET - DE11-341D3FN-N20N



Speed starters, three-phase power supply connection, three-phase motor connection at 400 V, 1, 3 A and 0, 37 kW / 0, 5 HP, with integrated EMC filter



Part no. Catalog No. Eaton Catalog No.

DE11-341D3FN-N20N 180662 . DE11-341D3FN-N20N

### Technical data General

General			
Standards			Specification for general requirements: IEC/EN 61800-2 EMC requirements: IEC/EN 61800-3 Safety requirements: IEC/EN 61800-5-1
Certifications			CE, UL, cUL, RCM
Production quality			RoHS, ISO 9001
Climatic proofing	ρ <sub>w</sub>	%	< 95%, average relative humidity (RH), non-condensing, non-corrosive
Ambient temperature			
operation (150 % overload)	9	°C	-10 - +60
Storage	9	°C	-40 - +70
Radio interference level			
Radio interference class (EMC)			C2, C3, depending on the motor cable length, the connected load, and ambient conditions. External radio interference suppression filters (optional) may be necessary.
Environment (EMC)			1st and 2nd environments as per EN 61800-3
maximum motor cable length	I	m	$\begin{array}{l} C2 \leq 10 \mbox{ m} \\ C3 \leq 25 \mbox{ m} \end{array}$
Mechanical shock resistance		g	15 (11 m/s, EN 60068-2-27)
Vibration			EN 61800-5-1
Altitude		m	0 - 1000 m above sea level Above 1000 m: 1% derating for every 100 m max. 2000 m
Degree of Protection			IP20/NEMA 0
Protection against direct contact			BGV A3 (VBG4, finger- and back-of-hand proof)
Main circuit			
Supply			
Rated operational voltage	U <sub>e</sub>		400 V AC, 3-phase 480 V AC, 3-phase
Mains voltage (50/60Hz)	U <sub>LN</sub>	V	380 (-10%) - 480 (+10%)
Input current (150% overload)	I <sub>LN</sub>	А	1.7
Supply frequency	f <sub>LN</sub>	Hz	50/60
Frequency range	f <sub>LN</sub>	Hz	45 - 66
Mains switch-on frequency			Maximum of one time every 30 seconds
Power section			
Overload current (150% overload)	I <sub>L</sub>	Α	1.95
max. starting current (High Overload)	I <sub>H</sub>	%	200
Note about max. starting current			for 1.875 seconds every 600 seconds
Output voltage with $\mathrm{V}_{\mathrm{e}}$	U <sub>2</sub>		400 V AC, 3-phase 480 V AC, 3-phase
Output Frequency	f <sub>2</sub>	Hz	0 - 50/60 (max. 300)
Switching frequency	f <sub>PWM</sub>	kHz	16 adjustable 4 - 32 (audible)
Operation Mode			U/f control Speed control with slip compensation
Frequency resolution (setpoint value)	Δf	Hz	0.03
Rated operational current			

At 150% overload	Ι <sub>e</sub>	А	1.3
Note			Rated operational current at an operating frequency of 16 kHz and an ambient air temperature of +50 $^\circ\mathrm{C}$
Maximum leakage current to ground (PE) without motor	I <sub>PE</sub>	mA	< 3.5 AC, < 10 DC
Fitted with			Radio interference suppression filter
Frame size			FS1
Motor feeder			
Note			for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm <sup>-1</sup> at 50 Hz or 1800 min <sup>-1</sup> at 60 Hz
Note			Overload cycle for 60 s every 600 s
Note			at 400 V, 50 Hz
150 % Overload	Р	kW	0.37
Note			at 440 - 480 V, 60 Hz
150 % Overload	Р	HP	0.5
Apparent power			
Apparent power at rated operation 400 V	S	kVA	0.9
Apparent power at rated operation 480 V	S	kVA	1.08
Braking function			
Standard braking torque			max. 30 % M <sub>N</sub>
DC braking torque			adjustable to 100 %
Control section			
Reference voltage	Us	V	10 V DC (max. 0.2 mA)
Analog inputs			1, parameterizable, 0 - 10 V DC, 0/4 - 20 mA
Digital inputs			4, parameterizable, 10 - 30 V DC
Relay outputs			1, parameterizable, N/O, 6 A (250 V, AC-1) / 5 A (30 V, DC-1)
Interface/field bus (built-in)			OP-Bus (RS485)/Modbus RTU, CANopen <sup>®</sup>
Assigned switching and protective elements			
Power Wiring			
Safety device (fuse or miniature circuit-breaker)			
IEC (Type B, gG), 150 %			FAZ-B6/3
UL (Class CC or J)		А	6
Mains contactor			
150 % overload (CT/I <sub>H</sub> , at 50 °C)			DILEM
110 % overload (VT/IL, at 40 °C)			DILM7
Main choke			
150 % overload (CT/I <sub>H</sub> , at 50 °C)			DX-LN3-004
Motor feeder			
motor choke			
150 % overload (CT/I <sub>H</sub> , at 50 °C)			DX-LM3-005

# Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	А	1.3
Heat dissipation per pole, current-dependent	P <sub>vid</sub>	W	0
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	18
Static heat dissipation, non-current-dependent	P <sub>vs</sub>	W	0
Heat dissipation capacity	P <sub>diss</sub>	W	0
Operating ambient temperature min.		°C	-10
Operating ambient temperature max.		°C	60
			Operation (with 150 % overload)
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.

10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0			
Low-voltage industrial components (EG000017) / Frequency converter =< 1 kV (EC001857)			
atic frequency converter	/ Static frequency converter = < 1 kv (ecl@ss8.1-27-02-31-01 [AKE177011])		
V	380 - 480		
	50/60 Hz		
	3		
	3		
Hz	300		
V	500		
А	1.3		
kW	0.5		
kW	0.5		
	No		
	Yes		
	Yes		
	No		
	Yes		
	No		
	Atic frequency converter V Hz V A kW		

Supporting protocol for SERCOS

Supporting protocol for EtherNet/IP

Supporting protocol for Foundation Fieldbus

Supporting protocol for AS-Interface Safety at Work

No

No

Yes

No

Supporting protocol for INTERBUS-SafetyNeSupporting protocol for PRDFisafeNoSupporting protocol for SafetyBUS pNoSupporting protocol for other bus systemsYesNumber of HW-interfaces industrial Ethernet0Number of HW-interfaces RS-R220Number of HW-interfaces RS-4220Number of HW-interfaces RS-4230Number of HW-interfaces RS-4240Number of HW-interfaces RS-4350Number of HW-interfaces RS-4360Number of HW-interfaces regrafied0Number of HW-interfaces other0Number of HW-interfaces otherNoNumber of HW-i			
Supporting protocol for PROFisefeNeSupporting protocol for SafetyBUS pNoSupporting protocol for other bus systemsYesNumber of HW-interfaces industrial Ethernet0Number of HW-interfaces RS-RDFINET0Number of HW-interfaces RS-2220Number of HW-interfaces RS-4230Number of HW-interfaces RS-4240Number of HW-interfaces RS-4350Number of HW-interfaces RS-4360Number of HW-interfaces serial TY0Number of HW-interfaces serial TY0Number of HW-interfaces other0Number of HW-interfaces otherNoNumber of HW-interfaces	Supporting protocol for DeviceNet Safety		No
Supporting protocol for SafetyBUS p     No       Supporting protocol for other bus systems     Yes       Number of HW-interfaces industrial Ethernet     0       Number of HW-interfaces PROFINET     0       Number of HW-interfaces SR-232     0       Number of HW-interfaces RS-422     0       Number of HW-interfaces SR-485     0       Number of HW-interfaces SR-485     0       Number of HW-interfaces serial TTY     0       Number of HW-interfaces SR-485     0       Number of HW-interfaces serial TTY     0       Number of HW-interfaces serial TTY     0       Number of HW-interfaces other     No       Numo	Supporting protocol for INTERBUS-Safety		No
Supporting protocol for other bus systems     Yes       Number of HW-interfaces industrial Ethernet     0       Number of HW-interfaces PROFINET     0       Number of HW-interfaces RS-232     0       Number of HW-interfaces RS-423     0       Number of HW-interfaces RS-435     0       Number of HW-interfaces RS-435     0       Number of HW-interfaces serial TTY     0       Number of HW-interfaces other     No       Number of HW-interfaces	Supporting protocol for PROFIsafe		No
Number of HW-interfaces industrial Ethernet     Image of HW-interfaces RS-DFINET     Image of HW-interfaces RS-232       Number of HW-interfaces RS-232     Image of HW-interfaces RS-232     Image of HW-interfaces RS-232       Number of HW-interfaces RS-232     Image of HW-interfaces RS-232     Image of HW-interfaces RS-232       Number of HW-interfaces RS-232     Image of HW-interfaces RS-232     Image of HW-interfaces RS-232       Number of HW-interfaces RS-232     Image of HW-interfaces RS-232     Image of HW-interfaces RS-232       Number of HW-interfaces RS-232     Image of HW-interfaces SS-232     Image of HW-interfaces SS-232       Number of HW-interfaces DSB     Image of HW-interfaces SS-232     Image of HW-interfaces SS-232       Number of HW-interfaces DSB     Image of HW-interfaces DSB     Image of HW-interfaces DSB       Number of HW-interfaces DSB     Image of HW-interfaces DSB     Image of HW-interfaces DSB       Number of HW-interfaces DSB     Image of HW-interfaces DSB     Image of HW-interfaces DSB       Number of HW-interfaces DSB     Image of HW-interfaces DSB     Image of HW-interfaces DSB       Number of HW-interfaces DSB     Image of HW-interfaces DSB     Image of HW-interfaces DSB       Number of HW-interfaces DSB     Image of HW-interfaces DSB     Image of HW-interfaces DSB	Supporting protocol for SafetyBUS p		No
Number of HW-interfaces PROFINET     Image of HW-interfaces RS-232     Image of HW-interfaces RS-232 <th< td=""><td>Supporting protocol for other bus systems</td><td></td><td>Yes</td></th<>	Supporting protocol for other bus systems		Yes
Number of HW-interfaces RS-232     Import of HW-interfaces RS-232     Import of HW-interfaces RS-232       Number of HW-interfaces RS-242     Import of HW-interfaces RS-242     Import of HW-interfaces RS-243       Number of HW-interfaces RS-243     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces RS-243     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces Strain TY     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces RS-243     Import of HW-interfaces RS-243       Number of HW-interfaces other     Import of HW-interfaces	Number of HW-interfaces industrial Ethernet		0
Number of HW-interfaces RS-422     Image of HW-interfaces RS-485     Image of HW-interfaces SRS-485       Number of HW-interfaces serial TTY     Image of HW-interfaces serial TTY     Image of HW-interfaces SRS-485       Number of HW-interfaces SRS-485     Image of HW-interfaces SRS-485     Image of HW-interfaces SRS-485       Number of HW-interfaces SRS-485     Image of HW-interfaces SRS-485     Image of HW-interfaces SRS-485       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Number of HW-interfaces SRS-481     Image of HW-interfaces SRS-481     Image of HW-interfaces SRS-481       Auge of HW-interfaces SRS-481     Imag	Number of HW-interfaces PROFINET		0
Number of HW-interfaces RS-485 I   Number of HW-interfaces serial TTY I   Number of HW-interfaces uSB I   Number of HW-interfaces parallel I   Number of HW-interfaces parallel I   Number of HW-interfaces other I   With PC connection I   Aquadrant operation possible I   Aquadrant operation possible I   Porter I   Ibight Imm   Yoth Imm   Yoth Imm	Number of HW-interfaces RS-232		0
Number of HW-interfaces serial TTY Image:	Number of HW-interfaces RS-422		0
Number of HW-interfaces USB   Image: State of the st	Number of HW-interfaces RS-485		1
Number of HW-interfaces parallel Image: Book of the state of the s	Number of HW-interfaces serial TTY		0
Number of HW-interfaces otherImage: Bit of the sector of the	Number of HW-interfaces USB		0
With optical interfaceModeWith PC connectionModeIntegrated breaking resistanceMode4-quadrant operation possibleModeType of converterModeDegree of protection (IP)ModeHeightModeWith ModeMod	Number of HW-interfaces parallel		0
With PC connectionModelIntegrated breaking resistanceModel4-quadrant operation possibleModelType of converterModelDegree of protection (IP)ModelHeightModelWith ModelModelWith ModelM	Number of HW-interfaces other		0
Integrated breaking resistance Image: Participation of the sector of t	With optical interface		No
4-quadrant operation possibleMoType of converterMoDegree of protection (IP)MoHeightMoWidthMmStateMmMo	With PC connection		No
Type of converter Mathematical Converter   Degree of protection (IP) Mathematical Converter   Height Mathematical Converter   Width Mathematical Converter	Integrated breaking resistance		No
Degree of protection (IP) mm 20   Height mm 20   Width mm 4	4-quadrant operation possible		No
Heightnm230Widthnm45	Type of converter		U converter
Width mm 45	Degree of protection (IP)		IP20
	Height	mm	230
Depth mm 168	Width	mm	45
	Depth	mm	168
Relative symmetric net frequency tolerance % 5	Relative symmetric net frequency tolerance	%	5
Relative symmetric net current tolerance % 10	Relative symmetric net current tolerance	%	10

## **Approvals**

Approvais	
Product Standards	UL 508C; CSA-C22.2 No. 14; IEC/EN61800-3; IEC/EN61800-5; CE marking
UL File No.	E172143
UL Category Control No.	NMMS, NMMS7
CSA File No.	UL report applies to both US and Canada
North America Certification	UL listed, certified by UL for use in Canada
Specially designed for North America	No
Suitable for	Branch circuits
Max. Voltage Rating	3~ 480 V AC IEC: TN-S UL/CSA: "Y" (Solidly Grounded Wey)
Degree of Protection	IEC: IP20

