

► Trenntransformator / AC Power Source

PeakTech® 2240



Unter dem Aspekt der hohen Sicherheitsanforderungen in den Service-Werkstätten, Schulen und der Industrie ist ein Trenntransformator eine absolute Voraussetzung, um fachgerechte Reparaturarbeiten durchzuführen. Eine galvanische Trennung zwischen Primär- und Sekundärspannung bei Messungen und Reparaturen an offenen Geräten garantiert einen hohen Sicherheitsstandard.

- Sicherheit: EN 61010-1
- Mit Schutzkontakt Ausgangsdose zum Anschluss von Schutzklasse 1 Geräten
- Zubehör: Netzkabel, Ersatzsicherung, Bedienungsanleitung

► SPECIFICATIONS

Eingangsspannung / Input voltage	230 V AC ~ 50/60 Hz
Ausgangsspannung / Output voltage	230 V AC ~ 50/60 Hz
Ausgangsleistung / Dauerstrom Output power / Continuous current	500 W / 2,5 A
Schutzklasse / Protection class	I (Gehäuse geerdet / case connected to PE)
Abmessungen / Dimensions (BxHxT/WxHxD)	160 x 125 x 235 mm
Gewicht / Weight	7,5 kg



Under consideration of the high safety requirements in the service centers, schools and industry it is absolutely necessary to use AC power source. This power source is provided with a galvanic separation between primary and secondary voltage for measuring and servicing of open instruments granting a high safety standard.

- Safety: EN 61010-1
- With earthed power outlet for connection of safety class 1 units
- Accessories: power cable, fuse and manual