



FUSE BOX EKM-200

FUSE BOX FOR APPLICATION IN LIGHTING POLES

KEY FEATURES

- Fulfills the requirements of VDE 0660-505 and DIN 43628
- Suitable for application in lighting poles with diameter ≥ 84 mm
- Fast installation thanks to improved, range taking cable sealings
- Proven mantle terminals allow simple and secure connection up to 16 mm^2
- Prewired with brass bars
- All metal parts corrosion protected
- Touch proof at maintenance even with removed cover

TE Connectivity's (TE) EKM-200 was developed to meet expectations with respect to ease of assembly and reliability. It is a cost effective solution to connect and protect luminaires in lighting poles.

With its mantle terminals EKM-200 can be installed fast and reliably in all street lighting grids.

Customers can count on consistent, high quality products, driven by TE's proven innovation and backed by our extraordinary customer support.



TECHNICAL DATA	
Detail	Data
Application range	inside of lighting poles
Pole inner diameter	≥ 84 mm
Min. dimension of hand hole W x H	70 x 240 mm
Degree of protection	IP 44
Protection class	II
Cable cross section feeder cable	up to 3 x 5 x 2,5 - 16 mm ² (cable dia. 2 x 10 - 24 mm or 3 x 10 - 23 mm)
Cable cross section luminaire cable	1 x 3 x 1,5 mm ² - 2 x 5 x 2,5 mm ² (cable dia. 8-14 mm)
Dimensions H x W x D	232 x 69 x 69
Feeder cable terminals	5 mantle terminals
Fuse system	2 X D01 (E14) with screw caps
Pinning	universal, L1, L2, L3, N, PE(N)
Protection against contact to life parts	acc. BGV A3
Material	thermoplastic material
Cover details	transparent cover with latch
Luminaire cable sealing	2 rubber glands, additionally 2 cables max. dia. 11,5 mm can be routed to the bottom

PRODUCT SELECTION INFORMATION					
Description		for 1 cable (mm ²)	for 2 cables (mm ²)	for 3 cables (mm ²)	Part Number
EKM-2020-2D1-B	2 fuseholders D01(E14), bulk packing 20 pcs.	5 x 2,5 - 16	5 x 2,5 - 16	5 x 2,5 - 16	512986-000
EKM-2020-2D1	2 fuseholders D01(E14)	5 x 2,5 - 16	5 x 2,5 - 16	5 x 2,5 - 16	919406-000
EKM-2020-2D1-6-E22-B	2 fuseholders D01(E14), 2 fuses 6 A, earthing cable 10 mm ² , green/yellow 400 mm long with screw M8x12	5 x 2,5 - 16	5 x 2,5 - 16	5 x 2,5 - 16	274608-000
Earthing cable for EKM-2020, length: 400 mm, green/yellow, 10 mm², HO7V-K					
GURO-EC10-RM8-400-S11	with cable sleeve for M11 mantle terminals, screw M8x12	-	-	-	EE0140-000
GURO-EC10-R8-400-S11	with cable sleeve for M11 mantle terminals, cable sleeve for M8	-	-	-	EE0135-000

te.com/energy

©2014 TE Connectivity Ltd. family of companies. All Rights Reserved. EPP-2355-10/14

TE Connectivity and TE connectivity (logo) are trademarks. Other logos, product and/or company names might be trademarks of their respective owners. While TE has made every reasonable effort to ensure the accuracy of the information in this brochure, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications.

FOR MORE INFORMATION: TE Technical Support Centers

USA:	+ 1 800 327 6996
France:	+ 33 380 583 200
UK:	+ 44 0870 870 7500
Germany:	+ 49 896 089 903
Spain:	+ 34 916 630 400
Benelux:	+ 32 16 351 731
Canada:	+ 1 (905) 475-6222
Mexico:	+ 52 (0) 55-1106-0800
Latin/S. America:	+ 54 (0) 11-4733-2200
China:	+ 86 (0) 400-820-6015